

XCFR2.E167040 - Terminal Blocks - Component

Terminal Blocks - Component

Switchlab Inc

8TH FL 66 CHUNG CHENG RD
HSIN CHUANG
TAIPEI HSIEN, 242 Taiwan

E167040

Cat. No.	Wire Range	Wire Type	FW	TQ Lb In.	V	A	UG	CA
T31 (@31)	22-16	Cu	2	12	300	10	B, D	2(120), 4
DPT2.5-PE, DPTN2.5-PE, DPT2.5/3-PE, DPTN2.5/3-PE, DPT2.5/4-PE, DPTN2.5/4-PE, followed by 1 thru 6 alphanumeric digits or blank.	26 - 12	Cu	2	N/A	600	NA (PCTB)	B	2 (105), 4
Cat. No. DPT1.5, followed by blank, /3 or /4, followed by 1 thru 6 alphanumeric digits or blank Cat. No. DPTN1.5, followed by blank, /3 or /4, followed by 1 thru 6 alphanumeric digits or blank	14 - 26	Cu	2	N/A	300	15	B	2 (105), 4
DPTN16-PE, DPTN16/3-PE, followed by 1 thru 6 alphanumeric digits or blank	4 - 20	Cu	2	N/A	600	—	B, C	2 (105), 4
T32 (@31)	22-16	Cu	2	12	300	15	B, D	2(120), 4
					150	15	C	
T33 (@31)	22-16	Cu	2	12	300	15	D	2(120), 4
T34 (@31)	22-12	Cu	2	12	300	25	D	2(120), 4
T35 (@31)	22-14	Cu	2	16	300	20	B, C, D	2(120), 4
T36 (@31)	22-12	Cu	2	16	300	25	B, C	2(120), 4
T42 (@31)	22-14	Cu	2	12	300	15	D	2(120), 4
OT42 (@31)	22-14	Cu	2	8	300	15	D	2(120)
469801-001-99	only stranded							4, #1

T44 (@31)	22-14	Cu	2	12	300	15	B, D	2(120), 4
					150	15	C	
MB (@31)	24-14	Cu	2	4	300	10	D	2(105), 4
MA (@31)	26-14	Cu	2	4	300	10	D	2(105), 4
MX(3), MX (4)	14-24	Cu	2	—	300	10	D	2(105)
MC(5)	14-24	Cu	2	4.5	300	12	D	2(105), 4
ME with 3.81 or 381 (2a)	—	Cu	1	—	300	12	D	2(105)
ME with 5.00, 500, 10.00 or 100 (2a)		Cu	1	—	300	16	B, D	2(105)
ME with 5.08 or 508 (2a)								
ME with 3.50 or 350 (2a)	—	Cu	1	—	150	12	B	2(105)
ME with 10.16 or 016 (2a)	—	Cu	2	7	300	16	B, C	2(105)
					600		D	
MD01, MD02(6)	16-24	Cu	2	3	300	15	B, D	2(105), 4
MD012(7) MD110, MD022 and MD122(8)	16-24	Cu	2	3	300	15	B, D	2(105), 4
TD1 (@31)	14-22	Cu	2	12	300	10	B, D	2(105), 4
TD4 (@31)	14-22	Cu	2	15	300	15	B, D	2(105), 4*
	14-22	Cu	1	15	300	20	B, D	2(105), 4*
MA212 (1)	16-26	Cu	2	2.5	300	6	B, D	2(105), 4*
MA332, MA412 (1)	12- 26(**)	Cu	2	4	300	16	B, D	2(105), 4*
MA522(1)	14-22	Cu	2	4	300	16	B, D	2(105), 4*
MB223(1D)	12-24	Cu	2	3.5	300	10	B, D	2(105), 4
MB310(@16), MB320 (1E),	12-26	Cu	2	5-7	300	16	B, D	2(105), 4*
MB360 (1E)								
MB312(@16), MB322 (1E)	12-26	Cu	2	5	300	16	B, D	2(105), 4*

MB362 (1E)								
MB332 (1E)	16-26	Cu	2	3	300	8	B, D	2(105), 4*
MB910 (1Eb), MB920 (1E)	10-24	Cu	2	9	600	Note A	D	2(105), 4*
					300	30	C	
MB910 (1Ec), MB910 (1Ea), MB912 (1Ed)	10-24	Cu	2	5.5- 9	600	Note A	D	2(105), 4*
					300	30	C	
MB422(1D)	12-24	Cu	2	6	300	28	B, D	
MB420(1D)	12-24	Cu	2	6	300	28	B, D	2(105), 4
MB912750(1F)	10-24	Cu	2	5.5	300	30	B, D	8(105), 4*
					150	—	C	
MB912635(1F), MB912762(1F)	10-24	Cu	2	5.5	300	30	B, D	2(105), 4*
MC100(1A), MC101(1A)	12-24	Cu	2	7	300	16	B, C	2(105), 4*, #20
MC200(1AA), MC211(1AA)								
MC210(1AA), MC201(1AA)								
MC100(1B), MC101(1B)	12-24	Cu	2	7	600	Note A	D	2(105), 4*, #20
MC200(1B), MC211(1B)								
MC210(1B), MC201(1B)								
MC100(1B), MC101(1B)					300	16	B, C	
MC200(1B), MC211(1B)								
MC210(1B), MC201(1B)								
MC100-762, MC101-762(@181)	12-24	Cu	2	4.5	300	15	B, D	2(105), 4*
					150	15	C	
ME010-762, ME020-762, ME030-762, ME040-762, ME050-762, ME060-762, ME070-762, ME080-762 (@181)	—	Cu	1	—	300	16	B, D	2(105)
					150	16	C	

MC420, MC421 (1C)	16-26	Cu	2	3	300	10	B, C	2(105), 4*
MB342 (@192)	14-28	Cu	2	4.5-6	300	15	B	2(115), 4
						Note A	D	
MPC310, MPC311, followed by 350 or 381, followed by 02 through 24, followed by one thru six alphanumeric digits or blank. MPC370 (@187)	16 - 24, str, sol	Cu	2	N/A	150	8	B	2 (115), 4, #20
	16 - 24, str, sol	Cu	1	N/A	50	8	C	2 (115), #20
MPC350, MPC351, followed by 350, followed by 04 through 34, followed by one thru six alphanumeric digits or blank.	16 - 24, str, sol	Cu	2	N/A	150	8	B	2 (115), 4, #20
	16 - 24, str, sol	Cu	1	N/A	50	8	C	2 (115), #20
ME253, ME263, followed by 350, followed by 04 through 40, followed by one thru six alphanumeric digits or blank.	-	-	1	N/A	150	8	B	2 (65), #20
	-	-	1	N/A	50	8	C	2 (65), #3, #20
ME233, ME243, followed by 04 through 40, followed by one thru six alphanumeric digits or blank.	-	-	1	N/A	300	10	B	2 (65), #3, #20
	-	-	1	N/A	50	10	C	2 (65), #3, #20
MPE930, MPE940, followed by 350, followed by 04 through 34, followed by one thru six alphanumeric digits or blank. MPE931(@188), MPE941(@188)	-	-	1	N/A	150	8	B	2 (115), #20
	-	-	1	N/A	50	8	C	2 (115), #20

Cat. No.	Wire Range	Wire Type	FW	TQ Lb In.	V	A	UG	CA
T14 (@116a)	12-22	Cu	2	10-12	300	25	B, D	2(140), 4
T24 (@31)	12-22	Cu	2	12	300	25	B, D	2(140), 4
T25 (@116)	12-22 (2)12-22	Cu	1 2	9.6-16	300	25 20	B, D	2(140), 4

T26 (@31)	12-22	Cu	1 2	16	300	25 20	B, D	2(140), 4
T30, T301 (@31)	16-30	Cu	2	10	300	10	B, D	2(120), 4
T30M (@31)	16-30	Cu	2	10	300	10	B, D	2(120), 4
T401, T40M (@31)	16-30	Cu	2	10	300	10	B, D	2(120), 4
T40 (@31)	16-30	Cu	2	8-10	300	10	B, D	2(120), 4
	16-30, Str. 22-30, Sol.	Cu	2	8-10	150	10	C	2(120), 4
T46M (@31)	14-22	Cu	1 2	16	300	22 15	B, D	2(120), 4
T64-W@	12-22	Cu	2	12	300	20	B, D	2(120), 4
T64-T@	12-22(**)	Cu	2	12	300	20	B, D	2(120), 4
T66-W, T66-AW@	14-22	Cu	1 2	12	300	25 15	B, D	2(120), 4
T66-T, T66-AT@	14-22(**)	Cu	1 2	12	300	25 15	B, D	2(120), 4
C31M, C41M	16-22	Cu	2	12	300	10	B, D	2(105), 4*
C34M	14-22	Cu	2	12	300	15	B, D	2(105), 4*
C44M (@31)	12-22	Cu	2	12	300	20	B	2(105), 4*
					300	Note A	D	
TA6 (@31)	10-18	Cu	2	14	600	30	B, C	2(120), 4*
	10-18	Cu	1	14	600	40	B, C	2(105), 4*
TA7 (@31)	10-18(**)	Cu	2	16	600	30	B, D	2(105), 4
MC31 -(1)	14-24	Cu	1	7	300	16	B, D	2(105), 4*
	14-24	Cu	2	7	300	15	B, D	2(105), 4*
MX622500(@189), MX622508(@189)	16-22	Cu	2	—	300	10	B, D	2(115), 4

MX622750(@189), MX622762(@189)	16-22	Cu	2	—	300	10	B, C	2(115), 4
MX522*350(@189), MX522-350(@189)	14-24, Sol. 16-24, Str.	Cu	2	—	300	6	B, D	2(115), 4*, Note 3
OMB362*500	12-24	Cu	2	—	300	15	B	2(105), 4*
T21(@43)	12-22, Sol/Str	Cu	2	8	300	10	B, D	2(140), 4*, (#1)
					100	10	C	
T21KO3D03TDR	12-22, Sol/Str	Cu	2	8	300	10	B, D	2(140), 4*, (#1)
T21(@184)	14-22	Cu	2	6~8	300	10	B, D	2(140), 4
					150	10	C	
T21(@185)	14-22	Cu	2	6~8	300	10	B, D	2(140), 4
					150	10	C	
MB612, MB622, MB632	14-26	Cu	2	4.5	300	16	B, D	2(105), 4
MB642, MB652, MB662 (@17)					150		C	
OMC021	14-24 Str/Sol	Cu	2	4.5	250	10	B, D	2(115), 4, #2
MWX100A, MWX100-250, MWX100B, MWX100-254	20-28	Cu	2	—	150	4	B	2(105), 4*
MWX101A, MWX101-250, MWX101B, MWX101-254								
MWX100E, MWX100-500, MWX100F, MWX100-508	14-28	Cu	1	—	300	16	B, D	2(105), 4
MWX101E, MWX101-500, MWX101F, MWX101-508								
MH120*O (@1)	6-26	Cu	1	20.5	300	65	B, C	2(115)
MA311, MA321 (@2)	14-26 Str/Sol	Cu	2	3	300	15	B, C	2(115), 4
MB332-DA, MB332-DB, MB332-DC (@1a)	16-26 Str/Sol	Cu	2	2	300	10	B	2(115), 4
MB332-381A, MB332-381B, MB332-381C (@1a)	16-26 Str/Sol	Cu	2	2	300	10	B	2(115), 4
MB424-508M(@104)	14-26	Cu	2	5.22	300	15	B	2(115), 4
MB424-508M (@140)	14-26	Cu	2	5.22	300	15	B	2(115), 4

					300	Note A	D	
MB522(@36)	16-26 Str/Sol	Cu	2	2	300	10	B	2(115), 4
MC420, MC421, OMC420, OMC421 (@4)	16-26 Str/Sol	Cu	2	3	300	10	B, D	2(115), 4, #3
ME030, ME040, ME050, ME060 (@4)	—	—	1	—	300	10	B, D	2(115), #3
ME230, ME240, ME250, ME252, ME260 (@5) ME230, ME240, ME250, ME252, ME260 (@158)	—	—	1	—	300	10	B, D	2(140), #3
ME230, ME240, ME250, ME252, ME260 (@141)	—	—	1	—	300	10	B	2(65), #3
ME230, ME240, ME250, ME252, ME260 (@159)	—	—	1	—	300	10	B	2(130), #3
MC230 (@6)	14-24 Str/Sol	Cu	2	4.5	300	16	B	2(115), 4, #4
ME010 (@6)	—	—	1	—	300	16	B	2(115), #4
MC100, MC110 (@205)	16-26, Str/Sol	Cu	2	3	300	10	B	2(115), 4, #3
MC520, MC521, MC560, MC561(@7)	16-24 Str/Sol	Cu	2	3	300	10	B, D	2(115), 4, #5
ME030, ME040(@7)	—	—	1	—	300	10	B, D	2(115), #5
MA331(@8)	14-26 Str/Sol	Cu	2	2.5	300	15	B, C	2(115), 4, Note 2
MB312(@8)	12-26 Str/Sol	Cu	2	5	300	16	B, C	2(115), 4, Note 2
MB332(@9)	16-26 Str/Sol	Cu	2	1.5 - 2.5	300	10	B, D	2(115), 4, Note 2
MB362(@10)	16-26 Str/Sol	Cu	2	1.5	300	10	B, D	2(115), 4, Note 2
MB422 (@11)	12-24 Str/Sol	Cu	2	5	300	27	B	2(115), 4, Note 2
MB422-750 (@59)	12-24 Str/Sol	Cu	2	5	300	27	B	2(115), 4, Note 2
MB422-762 (@59)	12-24 Str/Sol	Cu	2	5	300	27	B	2(115), 4, Note 2

MB432(@12)	12-24 Str/Sol	Cu	2	5	300	27	B	2(115), 4, Note 2
OMB432(@13)	12-24 Str/Sol	Cu	2	5	300	27	B	2(115), 4, Note 2
MX322-254	20-26 Str/Sol	Cu	2	—	150	5	B, D	2(115), 4
MX422-254	20-26 Str/Sol	Cu	2	—	150	5	B, D	2(115), 4
MC420(@14)	16-26 Str/Sol	Cu	2	2.5	300	12	B	2(115), 4, #6
ME430(@14)	16-26 Str/Sol	Cu	1	—	300	12	B	2(140), 4, #6
ME440(@14)	16-26 Str/Sol	Cu	1	—	300	12	B	2(140), 4, #6
MB220(@15)	12-24 Str/Sol	Cu	2	3.5	300	10	B, D	2(115), 4, Note 2
MB220(@15a)	12-24 Str/Sol	Cu	2	3.5	300	10	B, D	2(115), 4
MH120*016 (@27)	6-26 Str/Sol	Cu	2	20.5	300	65	B, C	2(115), 4
					600	Note A	D	
MH120-016 (@27)	6-26 Str/Sol	Cu	2	20.5	300	65	B, C	2(115), 4
					600	Note A	D	
MX732-500M (@1b)	14-22 Sol	Cu	2	—	300	8	B, D	2(115), 4
	14-22 Str					12	B	
					Note A	Note A	D	
CDU2.5	10-22 Str/Sol	Cu	2	7	600	24	B, C	2(115), 4
					Note A	Note A	D	
CDU4	8-22 Str/Sol	Cu	2	7.7	600	35	B, C	2(115), 4
					Note A	Note A	D	
CDU6	8-20 Str/Sol	Cu	2	14	600	50	B, C	2(115), 4

					Note A	Note A	D	
CDU10	6-16 Str/Sol	Cu	2	19	600	65	B, C	2(115), 4
					Note A	Note A	D	
MB910-635M(@103a)	10-24 Str/Sol	Cu	2	9	300	30	B	2(115),4
					Note A	Note A	D	
MB311-500M(@103)	12-24 Str/Sol	Cu	2	4	300	16	B	2(115), 4
					Note A	Note A	D	
CTR2.5-2, CTR2.5(@143)	12-22 Sol/Str	Cu	2	4.5	600	12	B, C	2(115), 4
					Note A	Note A	D	
CTR2.5A (@143)	12-22 Sol/Str	Cu	2	4.5	600	12	B, C	2(115), 4
					Note A	Note A	D	
CTR2.5D-2, CTR2.5D(@143)	12-22 Sol/Str	Cu	2	4.5	600	10	B, C	2(115), 4
					Note A	Note A	D	
CTR2.5AD (@143)	12-22 Sol/Str	Cu	2	4.5	600	10	B, C	2(115), 4
					Note A	Note A	D	
MD212-500(@18)	14-26 Sol/Str	Cu	1	3	300	10	B, D	2(115), #7
MD212-500(@93)	14-26 Sol/Str	Cu	2	3	300	10	B, D	2(115), 4, #7
MD022-500(@19)	—	—	1	—	300	10	B, D	2(115), #7
MD022-500(@93)	—	—	1	—	300	10	B, D	2(115), 4, #7
CDU2.5-3	10-22 Sol/Str	Cu	2	7	600	24	B, C	2(115), 4
					Note A	Note A	D	
CDU4-3	8-22 Sol/Str	Cu	2	7.7	600	35	B, C	2(115), 4

					Note A	Note A	D	
CDU6-3	8-20 Sol/Str	Cu	2	14	600	50	B, C	2(115), 4
					Note A	Note A	D	
CDU10-3	6-16 Sol	Cu	2	19	600	58	B, C	2(115), 4
					Note A	Note A	D	
CDU10-3	6-16 Str	Cu	2	19	600	65	B, C	2(115), 4
					Note A	Note A	D	
CDK2.5-2, CDK2.5(@143)	12-22 Str/Sol	Cu	2	5	600	20	B, C	2(115), 4
					Note A	Note A	D	
CDK2.5A(@143)	12-22 Str/Sol	Cu	2	5	600	20	B, C	2(115), 4
					Note A	Note A	D	
CDU16-1, CDU16(@143)	4-14 Str/Sol	Cu	2	31	600	78	B, C	2(115), 4
					Note A	Note A	D	
CDU35-1, CDU35(@143)	2-10 Str/Sol	Cu	2	51	1000	114	E	2(115), 4
CDU16-3	4-14 Str/Sol	Cu	2	31	600	78	B, C	2(115), 4
					Note A	Note A	D	
CPE2.5-1	12-26 Str/Sol	Cu	2	7	—	—	B, C	2(115), 4, #8
CPE4-1	10-26 Str/Sol	Cu	2	8.5	—	—	B, C	2(115), 4, #8
CPE6-1	8-26 Str/Sol	Cu	2	16	—	—	B, C	2(115), 4, #8
CPE10-1	6-16 Str/Sol	Cu	2	18			B, C	2(115), 4, #8
CPE16-1	6-14 Str/Sol	Cu	2	35	—	—	B, C	2(115), 4, #8

CPE35-1	2-10 Str/Sol	Cu	2	51	—	—	B, C	2(115), 4, #8
CPE2.5	12-26 Str/Sol	Cu	2	7	—	—	B, C	2(115), 4, #8
CPE4	10-26 Str/Sol	Cu	2	8.5	—	—	B, C	2(115), 4, #8
CPE6	8-26 Str/Sol	Cu	2	16	—	—	B, C	2(115), 4, #8
CPE10	6-16 Str/Sol	Cu	2	18	—	—	B, C	2(115), 4, #8
CPE16	6-14 Str/Sol	Cu	2	35	—	—	B, C	2(115), 4, #8
CPE35	2-10 Str/Sol	Cu	2	35	—	—	B, C	2(115), 4, #8
CPE2.5-3	12-26 Str/Sol	Cu	2	7	—	—	B, C	2(115), 4, #8
CPE4-3	10-26 Str/Sol	Cu	2	8.5	—	—	B, C	2(115), 4, #8
CPE6-3	8-26 Str/Sol	Cu	2	16	—	—	B, C	2(115), 4, #8
CPE10-3	6-16 Str/Sol	Cu	2	18	—	—	B, C	2(115), 4, #8
CPE16-3	6-14 Str/Sol	Cu	2	35	—	—	B, C	2(115), 4, #8
T68-T(@20)	10-22 Sol	Cu	1	14	600	30	B, C	2(140)
T68-W(@20A)	10-22 Str/Sol	Cu	2	14	600	30	B, C	2(140), 4
MB350-500(@21)	12-22 Str/Sol	Cu	2	4	300	16	B	2(115), 4
					Note A	Note A	D	
MH130-1505(@71)	1-20 Str	Cu	2	30	600	125	B, C	2(115), 4
					Note A	Note A	D	
MH131-1505(@19)	1-20 Str	Cu	2	30	600	125	B, C	2(115), 4
					Note A	Note A	D	
MC100(@22)	12-24 Sol/Str	Cu	2	5	300	16	B	2(115), 4, #9
					300	Note A	D	

MC200(@23)	12-24 Sol/Str	Cu	2	6	300	16	B	2(115), 4, #9
					300	Note A	D	
MC201(@23)	12-24 Sol/Str	Cu	2	6	300	16	V	2(115), 4, #9
					300	Note A	D	
MC310(@24)	12-24 Sol/Str	Cu	2	4.5	300	16	B	2(115), 4, #9
					300	Note A	D	
MC311(@24)	12-24 Sol/Str	Cu	2	4.5	300	16	B	2(115), 4, #9
					300	Note A	D	
ME110(@25)	—	—	1	—	300	16	B	2(115), #9, Note 4
					300	Note A	D	
ME110(@193)	—	—	1	—	300	16	B	2(115), #9
					300	Note A	D	
ME120(@25)	—	—	1	—	300	16	B	2(115), #9, Note 4
					300	Note A	D	
ME120(@193)	—	—	1	—	300	16	B	2(115), #9
					300	Note A	D	
ME130(@26)	—	—	1	—	300	16	B	2(115), #9, Note 5
					300	Note A	D	
ME130(@193)	—	—	1	—	300	16	B	2(115), #9
					300	Note A	D	

ME140(@26)	—	—	1	—	300	16	B	2(115), #9, Note 5
					300	Note A	D	
ME140(@193)	—	—	1	—	300	16	B	2(115), #9
					300	Note A	D	
ME150(@26)	—	—	1	—	300	16	B	2(115), #9, Note 5
					300	Note A	D	
ME150(@193)	—	—	1	—	300	16	B	2(115), #9
					300	Note A	D	
ME160(@26)	—	—	1	—	300	16	B	2(115), #9, Note 5
					300	Note A	D	
ME160(@193)	—	—	1	—	300	16	B	2(115), #9
					300	Note A	D	
ME210(@25)	—	—	1	—	300	16	B	2(115), #9, Note 4
					300	Note A	D	
ME220(@25)	—	—	1	—	300	16	B	2(115), #9, Note 4
					300	Note A	D	
ME230(@26)	—	—	1	—	300	16	B	2(115), #9, Note 4
					300	Note A	D	
ME240(@26)	—	—	1	—	300	16	B	2(115), #9, Note 4

					300	Note A	D	
ME250(@26)	—	—	1	—	300	16	B	2(115), #9, Note 4
					300	Note A	D	
ME260(@26)	—	—	1	—	300	16	B	2(115), #9, Note 4
					300	Note A	D	
MB910-635M(@28)	10-24 Sol/Str	Cu	2	9	300	28	B	2(115), 4
					300	Note A	D	
MC420-381(@29)	16-26 Sol/Str	Cu	1	2.5	300	10	B	2(115), #10
MC421-381(@29)	16-26 Sol/Str	Cu	1	2.5	300	10	B	2(115), #10
ME530-381(@30)	—	—	1	—	300	10	B	2(115), #10
ME540-381(@30)	—	—	1	—	300	10	B	2(115), #10
ME550-381(@30)	—	—	1	—	300	10	B	2(115), #10
ME560-381(@30)	—	—	1	—	300	10	B	2(115), #10
MC520-381(@29)	16-26 Sol/Str	Cu	1	3	300	9	B	2(115), #11
MC521-381(@29)	16-26 Sol/Str	Cu	1	3	300	9	B	2(115), #11
ME530-381(@30)	—	—	1	—	300	9	B	2(115), #11
ME540-381(@30)	—	—	1	—	300	9	B	2(115), #11
ME550-381(@30)	—	—	1	—	300	9	B	2(115), #11
ME560-381(@30)	—	—	1	—	300	9	B	2(115), #11
MC560-381(@29)	16-26 Sol/Str	Cu	1	3	300	9	B	2(115), #11
MC561-381(@29)	16-26 Sol/Str	Cu	1	3	300	9	B	2(115), #11

MX722-508(@40)	16-26 Str	Cu	1	—	300	10	B, D	2(115)
MC700-500(@133)	12-28, SOL	Cu	2	—	300	16	B	2(115), 4, #12
					300	Note A	D	
MC705-500(@133)	12-28, SOL	Cu	2	—	300	16	B	2(115), 4, #12
					300 Note A	D		
ME710-500(@32)	—	—	1	—	300	16	B	2(115), #12
					300	Note A	D	
ME720-500(@32)	—	—	1	—	300	16	B	2(115), 4, #12
					300	Note A	D	
ME730-500(@32)	—	—	1	—	300	16	B	2(115), #12
					300	Note A	D	
ME740-500(@32)	—	—	1	—	300	16	B	2(115), #12
					300	Note A	D	
ME735-500(@32)	—	—	1	—	300	16	B	2(115), #12
					300	Note A	D	
ME745-500(@32)	—	—	1	—	300	16	B	2(115), #12
					300	Note A	D	
MC700-100(@46)	12-28, SOL	Cu	2	—	300	16	B	2(115), 4, #12
					300	Note A	D	
MC705-100(@46)	12-28, SOL	Cu	2	—	300	16	B	2(115), 4, #12
					300	Note A	D	

ME710-100(@134)	—	—	1	—	300	16	B	2(115), #12
					300	Note A	D	
ME720-100(@134)	—	—	1	—	300	16	B	2(115), #12
					300	Note A	D	
ME730-100(@134)	—	—	1	—	300	16	B	2(115), #12
					300	Note A	D	
ME740-100(@134)	—	—	1	—	300	16	B	2(115), #12
					300	Note A	D	
MPX110-500(@29)	12-28, Sol/Str	Cu	2	—	300	15	B	2(115),4
					300	Note A	D	
MPX120-508(@29)	12-28, Str	Cu	2	—	300	10	B, D	2(115), 4
MPX130-508(@29)	12-28, Str	Cu	2	—	300	10	B, D	2(115), 4
MC600-350(@33)	18-22, Sol/Str	Cu	2	—	150	5	B	2(120), 4, #13
MC601-350(@33)	18-22, Sol/Str	Cu	2	—	150	5	B	2(120), 4, #13
MC605-350(@33)	18-22, Sol/Str	Cu	2	—	150	5	B	2(120), 4, #13
ME910-350(@33)	—	—	1	—	150	5	B	2(120), #13
ME920-350(@33)	—	—	1	—	150	5	B	2(120), #13
ME930-350(@33)	—	—	1	—	150	5	B	2(120), #13
ME940-350(@33)	—	—	1	—	150	5	B	2(120), #13
ME950-350(@33)	—	—	1	—	150	5	B	2(120), #13
ME960-350(@33)	—	—	1	—	150	5	B	2(120), #13
OMC600-350(@33)	18-22, Sol/Str	Cu	2	—	150	5	B	2(120), 4, #13

OMC601-350(@33)	18-22, Sol/Str	Cu	2	—	150	5	B	2(120), 4, #13
OMC605-350(@33)	18-22, Sol/Str	Cu	2	—	150	5	B	2(120), 4, #13
OME910-350(@33)	—	—	1	—	150	5	B	2(120), #13
OME920-350(@33)	—	—	1	—	150	5	B	2(120), #13
OME930-350(@33)	—	—	1	—	150	5	B	2(120), #13
OME940-350(@33)	—	—	1	—	150	5	B	2(120), #13
OME950-350(@33)	—	—	1	—	150	5	B	2(120), #13
OME960-350(@33)	—	—	1	—	150	5	B	2(120), #13
MC600-350(@168)	18-22, Sol/Str	Cu	2	—	150	5	B	2(115), 4, #13
MC601-350(@168)	18-22, Sol/Str	Cu	2	—	150	5	B	2(115), 4, #13
MC605-350(@168)	18-22, Sol/Str	Cu	2	—	150	5	B	2(115), 4, #13
ME910-350(@168)	—	—	1	—	150	5	B	2(115), #13
ME920-350(@168)	—	—	1	—	150	5	B	2(115), #13
ME930-350(@168)	—	—	1	—	150	5	B	2(115), #13
ME940-350(@168)	—	—	1	—	150	5	B	2(115), #13
ME950-350(@168)	—	—	1	—	150	5	B	2(115), #13
ME960-350(@168)	—	—	1	—	150	5	B	2(115), #13
OMC600-350(@168)	18-22, Sol/Str	Cu	2	—	150	5	B	2(115), 4, #13
OMC601-350(@168)	18 - 22, STR/SOL	Cu	2	—	150	5	B	2(115), 4, #13
OMC605-350(@168)	18-22, Sol/Str	Cu	2	—	150	5	B	2(115), 4, #13
OME910-350(@168)	—	—	1	—	150	5	B	2(115), #13

OME920-350(@168)	—	—	1	—	150	5	B	2(115), #13
OME930-350(@168)	—	—	1	—	150	5	B	2(115), #13
OME940-350(@168)	—	—	1	—	150	5	B	2(115), #13
OME950-350(@168)	—	—	1	—	150	5	B	2(115), #13
OME960-350(@168)	—	—	1	—	150	5	B	2(115), #13
CPE95	2-4/0, Str	Cu	2	106.5	—	—	B, C	2(115), 4, #8
OM15009-762(@34)	12-24, Sol/Str	Cu	2	4.5	300	15	B	2(115), 4, #14
					300	Note A	D	
OM15010-762(@34)	—	—	1	—	300	15	B	2(115), 4, #14
					300	Note A	D	
MC101-762(@35)	12-24, Sol/Str	Cu	2	4.5	300	15	B	2(115), 4, #15
					300	Note A	D	
ME050-762(@35)	—	—	1	—	300	15	B	2(115), #15
					300	Note A	D	
CPE50	6-1/0, Str	Cu	2	54	—	—	B, C	2(115), 4, #8
CDK4(@143)	10-22, Sol/Str	Cu	2	6	600	30	B, C	2(115), 4
CDK4A(@143)	10-22, Sol/Str	Cu	2	6	600	30	B, C	2(115), 4
CDK6(@143)	8-20, Sol/Str	Cu	2	14.5	600	41	B, C	2(115), 4
CDK10(@143)	6-16, Sol/Str	Cu	2	20	600	65	B, C	2(115), 4
CDU50(@143)	1/0-6, Str	Cu	2	53.5	1000	150	E	2(115), 4
CDU95(@143)	4/0-2, Str	Cu	2	150	1000	230	E	2(115), 4

MC200-750, MC210-750, MC201-750, MC211-750(@37)	12-24, Sol/Str	Cu	1	6	300	16	B	2(115), #16
					300	Note A	D	
ME010-750, ME020-750, ME030-750, ME040-750, ME050-750, ME060-750 (@37)	—	—	1	—	300	16	B	2(115), #16
					300	Note A	D	
MC310-508 (@38)	12-24, Sol/Str	Cu	1	4.5	300	16	B	2(115), #16
					300	Note A	D	
ME630-508 (@38)	—	—	1	—	300	16	B	2(115), #16
					300	Note A	D	
MWX30 (@39)	12-28, Sol/Str	Cu	2	—	300	20	B	2(115), 4
					300	Note A	D	
15264(@41)	12-26, Sol/Str	Cu	2	9	300	20	B	2 (130), 4, #17
						Note A	D	
15265(@41)	—	—	1	—	300	20	B	2 (120), #17
						Note A	D	
MX820, MX821, MX822(@42)	16-18 Sol, 16-20 Str	Cu	2	—	150	9	B	2 (140), 4
					300	9	D	
MB910-952(@44)	10-24, Sol/Str	Cu	2	9	300	30	B, C	2 (115), 4
					600	Note A	D	
MWX600, MWX601(@47)	16-20, SOL	Cu	2	—	300	6	B, D	2 (115), 4
MWX600, MWX601(@47)	16-20, STR(Soldered)	Cu	1	—	300	6	B, D	2 (115)
MC700-250(@48)	20-28, SOL/STR	Cu	2	—	150	4	B, D	2 (115), 4, #18
MC700-254(@48)	20-28, SOL/STR	Cu	2	—	150	4	B, D	2 (115), 4, #18

MC700-350(@49)	14-28, SOL/STR	Cu	2	—	300	10	B, D	2 (115), 4, #18
MC705-350(@49)	14-28, SOL/STR	Cu	2	—	300	10	B, D	2 (115), 4, #18
MC700-381(@49)	14-28, SOL/STR	Cu	2	—	300	10	B, D	2 (115), 4, #18
MC705-381(@49)	14-28, SOL/STR	Cu	2	—	300	10	B, D	2 (115), 4, #18
ME730-250(@50)	—	—	1	—	150	4	B, D	2 (115), #18
ME740-250(@50)	—	—	1	—	150	4	B, D	2 (115), #18
ME730-254(@50)	—	—	1	—	150	4	B, D	2 (115), #18
ME740-254(@50)	—	—	1	—	150	4	B, D	2 (115), #18
ME730-350(@50)	—	—	1	—	300	10	B, D	2 (115), #18
ME740-350(@50)	—	—	1	—	300	10	B, D	2 (115), #18
ME730-381(@50)	—	—	1	—	300	10	B, D	2 (115), #18
ME740-381(@50)	—	—	1	—	300	10	B, D	2 (115), #18
MB612(@51)	14-30, SOL/STR	Cu	2	4.5- 5.7	300	15	B	2(115), 4
MB622(@51)	14-30, SOL/STR	Cu	2	4.5- 5.7	300	15	B	2(115), 4
MB632(@51)	14-30, SOL/STR	Cu	2	4.5- 5.7	300	15	B	2(115), 4
MB642(@51)	14-30, SOL/STR	Cu	2	4.5- 5.7	300	15	B	2(115), 4
MB652(@51)	14-30, SOL/STR	Cu	2	4.5- 5.7	300	15	B	2(115), 4
MB662(@51)	14-30, SOL/STR	Cu	2	4.5- 5.7	300	15	B	2(115), 4
MD012-500M (@52)	14-24, SOL/ STR	Cu	2	3	300	15	B	2 (115), 4, #19
					300	Note A	D	
MD022-500(@52)	—	—	1	—	300	15	B	2 (115), #19

					300	Note A	D	
SPE2.5	12-28, SOL/STR	Cu	2	—	—	—	B, C	2 (115), 4
SPE2.5/3	12-28, SOL/STR	Cu	2	—	—	—	B, C	2 (115), 4
SPE2.5/4	12-28, SOL/STR	Cu	2	—	—	—	B, C	2 (115), 4
SPE4	12-28, SOL/STR	Cu	2	—	—	—	B, C(#)	2(115)
SPE4/3	12-28, SOL/STR	Cu	2	—	—	—	B, C(#)	2(115)
SPE4/4	12-28, SOL/STR	Cu	2	—	—	—	B, C(#)	2(115)
SPE6	10-24, SOL/STR	Cu	2	—	—	—	B, C(#)	2(115)
SPE6/3	10-24, SOL/STR	Cu	2	—	—	—	B, C(#)	2(115)
SPE10	8-24, SOL/STR	Cu	2	—	—	—	B, C(#)	2(115)
SPE10/3	8-24, SOL/STR	Cu	2	—	—	—	B, C(#)	2(115)
OM89001 (@53)	16-24, STR/SOL	Cu	2	—	300	2	B, D	2 (115), 4
OM89001 (@54)	16-24, STR/SOL	Cu	2	—	300	2	B, D	2 (115), 4
OM89001 (@55)	16-24, STR/SOL	Cu	2	—	300	2	B, D	2 (115), 4
OM89001 (@56)	16-24, STR/SOL	Cu	2	—	300	2	B, D	2 (115), 4
OM89001 (@57)	16-24, STR/SOL	Cu	2	—	300	2	B, D	2 (115), 4
OM89001 (@58)	16-24, STR/SOL	Cu	2	—	300	2	B, D	2 (115), 4
MA112 (@60) or (@61)	12-26, SOL/STR	Cu	2	4	300	15	B	2 (115), 4
						Note A	D	
MA114 (@62) or (@63)	12-26, SOL/STR	Cu	2	4	300	15	B	2 (115), 4
						Note A	D	

SDU2.5 (@64)	12-28, STR/SOL	Cu	2	—	600	18	B, C	2 (115), 4
						Note A	D	
SDU2.5/3 (@64)	12-28, STR/SOL	Cu	2	—	600	18	B, C	2 (115), 4
						Note A	D	
SDU2.5/4 (@64)	12-28, STR/SOL	Cu	2	—	600	18	B, C	2 (115), 4
						Note A	D	
SDU4 (@64)	12-28, STR/SOL	Cu	2	—	600	20	B, C	2 (115), 4
						Note A	D	
SDU4/3 (@64)	12-28, STR/SOL	Cu	2	—	600	20	B, C	2 (115), 4
						Note A	D	
SDU4/4 (@64))	12-28, STR/SOL	Cu	2	—	600	20	B, C	2 (115), 4
						Note A	D	
SDU6 (@64))	10-24, STR/SOL	Cu	2	—	600	30	B, C	2 (115), 4
						Note A	D	
SDU6/3 (@64)	10-24, STR/SOL	Cu	2	—	600	30	B, C	2 (115), 4
						Note A	D	
SDU10 (@64))	8-24, STR/SOL	Cu	2	—	600	38	B, C	2 (115), 4
						Note A	D	
SDU10/3 (@64))	8-24, STR/SOL	Cu	2	—	600	38	B, C	2 (115), 4
						Note A	D	
MPC300-500, MPC300H-500, MPC300-508, MPC300H-508, MPC301-500, MPC301H-500, MPC301-508, MPC301H-508(@65)	12-26, SOL/STR	Cu	2	—	300	16	B	2(115), 4, #20

					Note A	D		
ME010-500, ME010-508, ME020-500, ME020-508, ME030-500, ME030-508, ME040-500, ME040-508, ME050-500, ME050-508, ME060-500, ME060-508, ME070-500, ME070-508, ME080-500, ME080-508(@66)	—	—	1	—	300	16	B	2(115), #20
						Note A	D	
ME010-500, ME010-508, ME030-500, ME030-508, ME050-500, ME050-508(@180a)	—	—	1	—	300	16	B	2(115), #20
						Note A	D	
ME010-100, ME010-016, ME030-100, ME030-016, ME050-100, ME050-016(@180b)	—	—	1	—	300	16	B	2(115), #20
						Note A	D	
ME010-100, ME010-016, ME020-100, ME020-016, ME030-100, ME030-016, ME040-100, ME040-016, ME050-100, ME050-016, ME060-100, ME060-016, ME070-100, ME070-016, ME080-100, ME080-016 (@37a)	—	—	1	—	300	16	B	2(115), #20
						Note A	D	
ME050-508(@169), ME060-508(@169)	—	—	1	—	300	16	B	2(75), #20
						Note A	D	
MPC300-762 (@37b)	12-26, SOL/STR	CU	2	—	300	20	B, C	2(115), 4, #20
					600	Note A	D	
MPC300-750, MPC300-762, MPC301-750, MPC301- 762(@37a)	12-26, SOL/STR	Cu	2	—	300	16	B	2(115), 4, #20
						Note A	D	
ME030-762, ME040-762 (@37b)	—	—	1	—	300	20	B, C	2(115), #20
					600	Note A	D	
ME010-750, ME020-750, ME030-750, ME040-750, ME050-750, ME060-750, ME070-750, ME080-750, ME010-762, ME020-762, ME030-762, ME040-762, ME050-762, ME060-762, ME070-762, ME080- 762(@37a)	—	—	1	—	300	16	B	2(115), #20

						Note A	D	
MXC200-500, MXC200-508 (@209)	16-28, SOL/STR	Cu	2	—	300	10	B, D	2(115), 4, #20
MDC210-500 (@66)	12-30, SOL/STR	Cu	2	—	300	16	B, D	2(110), 4, #20
CDU2.5N (@67), CDU2.5NA (@67)	12-28, Str/Sol	Cu	2	5 (&)	600 (#)	20	B, C	2 (115), 4
CDU2.5NB (@190)	12-28	CU	2	4~5	600	20	B, C	2 (115), 4
CDU4N (@67), CDU4NA (@67)	10-22, Str/Sol	Cu	2	10 (&)	600 (#)	30	B, C	2 (115), 4
CDU4NB (@190)	10-26	CU	2	4.5~5	600	30	B, C	2 (115), 4
CDU6N (@67), CDU6NA (@67)	8-26, Str/Sol	Cu	2	14 (&)	600 (#)	50	B, C	2 (115), 4
CDU10N (@67), CDU10NA (@67)	6-24, Str/Sol	Cu	2	19 (&)	600 (#)	65	B, C	2 (115), 4
CDU2.5/3N (@143), CDU2.5/4N (@143)	28-12, Sol/Str	Cu	2	4-4.5	300	20	B	2(115), 4
					300	Note A	D	
CDU4/3N (@143), CDU4/4N (@143)	28-10, Sol/Str	Cu	2	5.6.2	300	30	B	2(115), 4
					300	Note A	D	
OTA3001(Pole 1, Pole 5 thru Pole 13)	4 - 10, SOL/STR	Cu	2	30.4	600	85	B, C	2(115), 4
OTA3001(Pole 2 and Pole 3)	4 - 10, SOL/STR (Note 1)	Cu	2	39	600	85	B, C	2(115), 4
OTA3001(Pole 4)	4 - 10, SOL/STR (Note 1)	Cu	2	30.4	600	85	B, C	2(115), 4
MWX400-500, MWX400-350 (@68), MWX400-35007A8101, MWX400-35007A8102	20-16, SOL	Cu	2	—	300	10	B, D	2 (115), 4
MPX221-500(@69)	22-14, STR/SOL	Cu	2	—	300	10	B, D	2 (115), 4
SDUB1.5 (@70)	28-16, STR/SOL	Cu	2	—	300	10	B, C	2 (115), 4
SDUB1.5/2(@142), SDUS1.5(@142), SDUS1.5/2 (@142)	28-16, STR/SOL	Cu	2	—	300	10	B, D	2 (115), 4
					150	10	C	

SDUB2.5(@70), SDUB2.5/2(@142), SDUS2.5(@142), SDUS2.5/2 (@142)	28-14, STR/SOL	Cu	2	—	300	15	B, C	2 (115), 4
MZ700-500 (@72)	28-12, STR/SOL	Cu	2	—	300	16	B	2 (115), 4, #21
					300	Note A	D	
MZ701-500 (@72)	28-12, STR/SOL	Cu	2	—	300	16	B	2 (115), 4, #22
					300	Note A	D	
MC700-500 (@73)	24-14, STR/SOL	Cu	2	—	300	15	B	2 (115), 4, #21, #22
					300	Note A	D	
MC700-500 (@194)	28-12, SOL/STR	Cu	2	—	300	16	B	2 (115), 4, #21, #22
					300	Note A	D	
MB552 (@74)	16 - 30, SOL/STR	Cu	2	2.2	300	10	B	2(115), 4
MB552 (@84)	16 - 30, SOL/STR	Cu	2	2.2	300	10	B, D	2(115), 4
MWX1 (@75)	12-28, SOL/STR	Cu	2	—	300	16	B	2 (115), 4
					300	Note A	D	
MA524 (@76)	12-22, SOL/STR	Cu	2	4	300	16	B	2 (115), 4
MB612 (@77)	14-30, SOL/STR	Cu	2	4.5	300	15	B	2 (115), 4
					300	Note A	D	
MB912 (@78)	10-24, SOL/STR	Cu	2	5.5	300	30	B, C	2 (115), 4
					300	Note A	D	
MWX410-500 (@79)	16-24, SOL/STR	Cu	2	—	300	7.5	B, D	2 (115), 4
OM89001-E (@87)	16-24, SOL/STR	Cu	2	—	300	7.5	B, D	2 (115), 4
MWX420-500 (@183)	16-24	Cu	2	—	300	7.5	B, D	2 (115), 4

MWX420-508 (@183)	16-24	Cu	2	—	300	7.5	B, D	2 (115), 4
MH110-016 (@80)	6-20, SOL/STR	Cu	2	20	300	57	B	2 (115), 4
					300	Note A	D	
MH110-016 (@81)	6-20, SOL/STR	Cu	2	20	300	57	B, C	2 (115), 4
					600	Note A	D	
MH110-016M (@82)	6-20, SOL/STR	Cu	2	20	300	57	B	2 (115), 4
					300	Note A	D	
MH110-016M (@83)	6-20, SOL/STR	Cu	2	20	300	57	B, C	2 (115), 4
					600	Note A	D	
MH110-016 (@95)	6-20, SOL/STR	Cu	2	20	600	57	B, C	2(115), 4
					600	Note A	D	
MPC300, MPC301 (@7a)	28-16, STR/SOL	Cu	2	—	300	8	B	2 (115), 4, #23
ME030, ME050 (@7a)	—	—	1	—	300	8	B	2 (115), #23
MH140-635M7 (@85), MH140-635M8 (@85), MH150-635M7 (@85), MH150-635M8 (@85)	8-18 SOL/STR	Cu	2	9	600	35	B, C	2(115), 4
					600	Note A	D	
MH140-6357 (@86), MH140-6358 (@86), MH150-6357 (@86), MH150-6358 (@86)	8-18 SOL/STR	Cu	2	9	600	35	B, C	2(115), 4
					600	Note A	D	
MH140-6357 (@96), MH140-6358 (@96), MH150-6357 (@96), MH150-6358 (@96)	8-18 SOL/STR	Cu	2	5-7	600	35	B, C	2(115), 4
					600	Note A	D	
MH140-6357 (@170), MH140-6358 (@170),	8-24 SOL/STR	Cu	2	9-13- 2	600	35	B, C	2(115), 4
					600	Note A	D	

OM57001	1/0-6	Cu	2	88.5	600	120	B, C	2(115), 4
						Note A	D	
MB53 (@88)	24-10, STR/SOL	Cu	2	6.0	300	25	B, C	2 (115), 4
					300	Note A	D	
MB43 (@89)	24-10, STR/SOL	Cu	2	6.0	300	25	B, C	2 (115), 4
					300	Note A	D	
MB42 (@90)	24-10, STR/SOL	Cu	2	6.0	300	25	B, C	2 (115), 4
					300	Note A	D	
CTR4SI/EN (@91), CTR4SF/EN (@91)	22-10, STR/SOL	Cu	2	7.7	600	7.5	B, C	2 (115), 4
					600	Note A	D	
CTR4SI/EN-1(@91)	22-10, STR/SOL	Cu	2	7.7	600	7.5	B, C	2 (115), 4
					600	Note A	D	
MX832 (@92)	20-14, STR/SOL	Cu	2	—	300	12	B	2 (105), 4
						Note A	D	
MT300 (@94), MT310 (@94)	24-12 SOL/STR	Cu	2	4.5	300	20	B	2(115), 4
						Note A	D	
MA126-500 (@126), MA126-500M (@126)	12~26, SOL/STR	Cu	2	3.54	300	15	B	2 (115), 4
						Note A	D	
MC (@97)	24-16, STR/SOL	Cu	2	3	300	8	B, D	(115), 4, #24
ME (@98)	—	—	1	—	300	8	B, D	2 (115), #24
MH140 (@99), (@100)	20-6, STR/SOL	Cu	2	15	600	60	B, C	2 (115), 4

					600	Note A	D	
BCM100 (@101)	10-22, SOL/STR	Cu	2	4.4	300 (#25)	30	B	2(115), 4
					150 (#25)	30	C	
BCM101 (@102)	10-22, SOL/STR	Cu	2	4.4	300 (#25)	30	B (#26)	2(120), 4
CDU2.5M (@103)	22-12, STR/SOL	Cu	2	5	300 (#)	20	B, C	2(115), 4
					600 (#)	Note A	D	
MWX (@105), MWX (@182)	20-10	Cu	2	—	300	25	B	2 (115), 4
				—	150	25	C	
				—	300	Note A	D	
MWX (@106), MWX (@182a)	20-10	Cu	2	—	300	25	B, C	2 (115), 4
				—	600	Note A	D	
SDK2.5 (@107)	12-28, STR/SOL	Cu	2	—	600 (#)	20	B, C	2(115), 4
					600 (#)	Note A	D	
MD512-500 (@108)	22-12, STR/SOL	Cu	2	3.5	300	12	B	2 (115), 4, #27
MD122-500 (@108)	—	—	1	—	300	Note A	D	2 (115), #27
MWX200, MWX201 (@109)	20-14, STR/SOL	Cu	2	—	300	10	B, D	2 (115), 4
MWX220 (@110), MWX211 (@110a)	20-14, STR/SOL	Cu	2	—	300	10	B, D	2 (115), 4
MWX200, MWX201 (@111)	20-16, STR	Cu	2	—	300	8	B, D	2 (115), 4
MPZ100 (@112)	26-20, STR/SOL	Cu	2	5.3	300	5	B, D	2 (115), 4, #28
MF300 (@112)	26-20, STR/SOL	Cu	2	—	300	5	B, D	2 (120), 4, #28
MB800-500 (@113)	28-14, STR/SOL	Cu	2	5.3	300	15	B	2 (115), 4
					300	Note A	D	

BCM080 (@114)	22-12, STR/SOL	Cu	2	5.5	300 (#29)	20	B (#29)	2 (115), 4
					300 (#30)	Note A	D (#30)	
MA212-350M (@115)	26-16, STR/SOL	Cu	2	2	300	6	B	2 (115), 4, Note 2
MA212-350 (@152)	26-16, STR/SOL	Cu	2	2	300	6	B	2 (115), 4
MC420 (@117)	26-16, STR/SOL	Cu	2	2.5	300	8	B, D	2 (115), 4, #31
ME630 (@118)	—	—	1	—	300	8	B, D	2 (115), #31
MC421 (@117)	26-16, STR/SOL	Cu	2	2.5	300	8	B, D	2 (115), 4, #32
ME631 (@118)	—	—	1	—	300	8	B, D	2 (115), #32
SDUN (@119), (@120)	12-28, Sol/Str	Cu	2	—	600	15.1	B, C	2(115), 4
					600	Note A	D	
MX432-254 (@121)	20-28, Sol/Str	Cu	2	—	150	5	B	2(115), 4
MX442-254 (@121)	20-28, Sol/Str	Cu	2	—	150	5	B	2(115), 4
TA7 (@122), (@123)	18-8, STR/SOL	Cu	2	12	600	40	B, C	2 (115), 4
TA7 (@124), (@125)	18-8, STR/SOL	Cu	2	12	300	40	B, C	2 (115), 4
					600	Note A	D	
MWX701 (@127)	12-24, Sol/Str	Cu	2	—	300	16	B	2 (115), 4
					300	Note A	D	
MWX701 (@128)	12-24, Sol/Str	Cu	2	—	300	11	B	2 (115), 4
					300	Note A	D	
SPE16 (@129)	4-16, SOL/STR	Cu	2	—	600	—	B, C	2 (115), 4
SDU16 (@130)	4-16	Cu	2	—	600	66	B, C	2 (115), 4

TFDM-A (@103)	10-20, SOL/STR	Cu	2	18	600	30	B, C	2(115), 4
					600	Note A	D	
MX522 (@131)	20-26, Sol/Str	Cu	2	—	300	5	B	2(115), 4
CTR4(@143)	10-22 sol/str	Cu	2	6	600	22	B, C	2 (115), 4
CTR4A(@143)	10-22 sol/str	Cu	2	6	600	22	B, C	2 (115), 4
CTR4D(@143)	12-22 sol/str	Cu	2	6	600	16	B, C	2 (115), 4
CTR4AD(@143)	12-22 sol/str	Cu	2	6	600	16	B, C	2 (115), 4
CTR4SB(@143)	12-22 sol/str	Cu	2	6	600	16	B, C	2 (115), 4
CTR4ASB(@143)	12-22 sol/str	Cu	2	6	600	16	B, C	2 (115), 4
CTR4SF(@143)	14-22 sol/str	Cu	2	6	600	15	B, C	2 (115), 4
CTR4ASF(@143)	14-22 sol/str	Cu	2	6	600	15	B, C	2 (115), 4
CTR4SI(@143)	14-22 sol/str	Cu	2	6	600	15	B, C	2 (115), 4
CTR4ASI(@143)	14-22 sol/str	Cu	2	6	600	15	B, C	2 (115), 4
TDE-1241 (@132)	12-24 sol/str, unprepared	Cu	2	7-9; 9- 12.3	300	20	B, C, D	2(140), 4
	10-24 sol/str, prepared							2(140), 5
MPC100-762(zz), MPC101-762(zz)	30-10 sol/str	Cu	2	5.3	300	30	B	2(115), 4
					150	30	C	
					300	Note A	D	
MPE100-762(zz), MPE101-762(zz)	—	—	1	—	300	30	B	2(115)
					150	30	C	
					300	Note A	D	
MPE120-762(zz), MPE121-762(zz)	—	—	1	—	300	30	B, C	2(115)

					300	Note A	D	
MPC101H-016(z), MPC100H-016(z)	8-20 sol/str	Cu	2	13.3	600	50	B, C	2(115), 4
						Note A	D	
MPE100-016(z), MPE101-016(z)	—	—	1	—	300	50	B, C	2(115)
					600	Note A	D	
MPE120-016(z), MPE121-016(z)	—	—	1	—	300	50	B, C	2(115)
					600	Note A	D	
MPC100H-762(z), MPC101H-762(z)	30-10 sol/str	Cu	2	5.3	600	30	B, C	2(115), 4
MPE100-7627 (zz)	—	—	1	—	600	30	B, C	2(140)
					600	Note A	D	
MPE100-7628 (zz)	—	—	1	—	600	30	B, C	2(140)
					600	Note A	D	
MPE100-762C (zz)	—	—	1	—	600	30	B, C	2(140)
					600	Note A	D	
MPE100-762D (zz)	—	—	1	—	600	30	B, C	2(140)
					600	Note A	D	
MPZ100-508 (@150)	12-30, Sol/Str	Cu	2	5.3	300	16 10	B D	2(115), 4
MPZ100-500 (@150)	12-30, Sol/Str	Cu	2	5.3	300	16 10	B D	2(115), 4
MPZ101-508 (10)	12-30, Sol/Str	Cu	2	5.3	300	16 10	B D	2(115), 4
MPZ102-508 (@150)	12-30, Sol/Str	Cu	2	5.3	300	16 10	B D	2(115), 4
MC101-508 (2)	12-30, Sol/Str	Cu	2	5.3-7	300	16 10	B D	2(115), 4
MC800-508 (9)	12-30, Sol/Str	Cu	2	4.5	300	16 10	B D	2(115), 4
MB260-508 w/wo M (10)	12-24, Sol/Str	Cu	2	3.5	300	10	B, D	2(115), 4

MB260-500 w/wo M (10)	12-24, Sol/Str	Cu	2	3.5	300	10	B, D	2(115), 4
MB312-254 (2), w/wo N1P	18-30, Sol/Str	Cu	2	1.32	150	6	B	2(115), 4
MF203-508 (10)	N/A	Cu	1	N/A	300	16 10	B D	2(115)
MF204-508 (10)	N/A	Cu	1	N/A	300	16 10	B D	2(115)
ME020-508 (9)	N/A	Cu	1	N/A	300	16 10	B D	2(115)
ME860-508 (2)	N/A	Cu	1	N/A	300	16 10	B D	2(115)
MF100-500 (@150)	N/A	Cu	1	N/A	300	16 10	B D	2(115)
MF100-508 (@150)	N/A	Cu	1	N/A	300	16 10	B D	2(115)
MF101-500 (@150)	N/A	Cu	1	N/A	300	16 10	B D	2(115)
MF101-508 (@150)	N/A	Cu	1	N/A	300	16 10	B D	2(115)
CTL6 (@161), CTL6-2 (@161)	8-22 SOL/STR	Cu	2	14	300	45	B, C	2(115), 4
					300	Note A	D	
MPC300-250 (X1) (X2), ME030-250 (X1) (X2) and ME040-250 (X1) (X2)	20-28 SOL/STR	Cu	2	—	150	4	B	2(115)
SDUB4 (@135)	12-28, Sol/Str	Cu	2	—	300	20	B, C	2(115), 4
					300	Note A	D	
SDUB4/2 (@135)	12-28, Sol/Str	Cu	2	—	300	20	B, C	2(115), 4
					300	Note A	D	
SDUS4 (@135)	12-28, Sol/Str	Cu	2	—	300	20	B, C	2(115), 4
					300	Note A	D	
SDUS4/2 (@135)	12-28, Sol/Str	Cu	2	—	300	20	B, C	2(115), 4
					300	Note A	D	

T68-W@	10-22	Cu	2	14	300	30	B, D	2(140), 4
T68-T@	10-22(**)	Cu	2	14	300	30	B, D	2(140), 4
MB312-381 (@136)	16-26, Sol/Str	Cu	2	1.9	300	10	B	2(115), 4
T4BBJ1Q (@137)	12-14, Sol/Str	Cu	2	12-14	600	20	B, C	2(125), 5
	16-18, Sol/Str	Cu	2	12-14	600	10	B, C	2(125), 4
T4DBI10 (@138)	8-18, Sol/Str	Cu	2	15.9	600	45	B, C	2(125), 5
T4DBJ10 (@138)	8-18, Sol/Str	Cu	2	15.9	600	45	B, C	2(125), 5
TBCM-W (@139)	2-14	Cu	2	22.1	600	115	B, C	2(130), 5
TBFM-W (@139)	1-8	Cu	2	26.9	600	130	B, C	2(140), 5
OT40004 (@143)	6-10	Cu	2	44.3	600	65	B, C	2(115), 4
	4	Cu	2	30	600	80	B, C	2(115), 5
OT40003 (@143) (Front)	1/0-8	Cu	2	78.2	600	130	B, C	2(115), 4
OT40003 (@143) (Back side of Pole 11, 12, tang connector with threaded hole)				30.4				
CPE2.5N (@143)	12-28, SOL/STR	Cu	2	4-5.2	600	—	B, C	2(115), 4, #8
CPE4N (@143)	10-26, SOL/STR	Cu	2	5-6.2	600	—	B, C	2(115), 4, #8
CPE6N (@143)	8-26	Cu	2	10-14	600	—	B, C	2(115), 4, #8
CPE10N (@143)	6-24	Cu	2	13-16	600	—	B, C	2(115), 4, #8
TBGM-W (@144)	2/0-10	Cu	2	26.9	600	150	B, C	2(140), 5
DST2.5, DST2.5/3, DST2.5/4 (@145)	12-28	Cu	2	—	600	20	B, C	2(115), 4
DST2.5-3L (@145)	12-28	Cu	2	—	300	20	B, C	2(115), 4
	12-28	Cu	2	—	600	Note A	D	2(115), 4

DSPB2.5/ (@156)	12-28 AWG	Cu	2	—	300	20	B, C	2(115), 4, #20
				—	600	Note A	D	
DST2.5/1P (@157)	12-28 AWG	Cu	2	—	600	20	B, C	2(115), 4, #20
DSTTB2.5 (@145)	12-28	Cu	2	—	600	20	B, C	2(115), 4
DSTTB2.5/3 (@145)	12-28	Cu	2	—	300	20	B	2(115), 4
					150	20	C	
					300	Note A	D	
DST1.5 (@145), DST1.5/3 (@145), DST1.5/4 (@145)	14-28	Cu	2	—	600	15	B, C	2(115), 4
DST4, DST4/3, DST4/4 (@145)	10-28	Cu	2	—	600	30	B, C	2(115), 4
DSTTB2.5-PE (@145)	12-28	Cu	2	—	600	—	B, C	2(115), 4
DST2.5-PE, DST2.5/3-PE, DST2.5/4-PE (@145)	12-28	Cu	2	—	600	—	B, C	2(115), 4
MPX315-1505 (@108)	4-18	Cu	2	—	600	66	B, C	2(115), 4
MPX315-1005 (@171)	6-18	Cu	2	—	300	51	B	2(115), 4
					150	51	C	2(115), 4
MPX315-100 (@172)	6-18	Cu	2	—	600	51	B, C	2(115), 4
DPT1.5-PE (@143), DPT1.5/3-PE (@143), DPT1.5/4-PE (@143), DPTN1.5-PE (@143), DPTN1.5/3-PE (@143), DPTN1.5/4-PE (@143)	14-26	Cu	2	—	300	—	b, c	2(115), 4
DST1.5-PE (@145)	14-28	Cu	2	—	600	—	B, C	2(115), 4
DPT4-PE (@143), DPT4/3-PE (@143), DPT4/4-PE (@143), DPTN4-PE (@143), DPTN4/3-PE (@143), DPTN4/4-PE (@143)	10-24	Cu	2	—	600	—	B, C	2(115), 4
DPT6-PE (@143), DPT6/3-PE (@143), DPT6/4-PE (@143), DPTN6-PE (@143), DPTN6/3-PE (@143), DPTN6/4-PE (@143)	8-20	Cu	2	—	600	—	B, C	2(115), 4
DPT10-PE (@143), DPT10/3-PE (@143), DPTN10-PE (@143), DPTN10/3-PE (@143)	6-20	Cu	2	—	600	—	B, C	2(115), 4
DSTTB4 (@145)	10-28	Cu	2	—	600	30	B, C	2(115), 4

DST4-PE(@145), DST4/3-PE(@145), DST4/4-PE (@145)	10-28	Cu	2	—	600	—	B, C	2(115), 4
DST4-HEDI(@145), DST4-HESI(@145), DST4-HESILED24(@145), DST4-HESILED60(@145), DST4-HESILED250 (@145)	10-28	Cu	2	—	600	10	B, C	2(115), 4
DST2.5-MT (@145)	12-28, Sol	Cu	2	—	600	16	B, C	2(115), 4
	12-28, Str	Cu	2	—	600	18	B, C	
DST4-MT (@145)	10-28	Cu	2	—	600	21	B, C	2(115), 4
MPX312-7504 (@146)	10-24	Cu	2	—	300	30	B, C	2(115), 4
MPX312-7507 (@147), MPX312-7508 (@147)	10-24	Cu	2	—	600	30	B, C	2(115), 4
DST10-PE (@145)	6-24	Cu	2	—	600	—	B, C	2(115), 4
OMA3001 (@143)	6	Cu	2	39	150	57	B, C	2(130), 5
OMARI001	6	Cu	2	60	300	75	B, D	2(130), 5
OMARI004 (@143)	2	Cu	2	60	300	130	B	2(130), 5
OMARI005 (@143)	2	Cu	2	60	150	115	B	2(130), 5
DST10 (@145)	6-24	Cu	2	—	600	65	B, C	2(115), 4
DST16 (@145)	4-24	Cu	2	—	600	80	B, C	2(115), 4
DST6-PE(@145), DST6/3-PE(@145)	8-24	Cu	2	—	600	—	B, C	2(115), 4
DST16-PE(@145)	4-24	Cu	2	—	600	—	B, C	2(115), 4
MJ101-850 (@148)	8-14	Cu	2	(&1)	600	50	B, C	2(115), 4
DST6 (@145), DST6/3 (@145)	8-24	Cu	2	—	600	48	B, C	2(115), 4
TB7-W (@149)	8-22	Cu	2	16	600	50	B, C	2(130), 4
MH180-1505 (@151)	1-20	Cu	2	33.6- 35.4	600	127	B, C	2(120), 4
DSTTB2.5V (@145)	12-28	Cu	2	—	600	20	B, C	2(115), 4

DPT2.5 (@143), DPT2.5/3 (@143), DPT2.5/4 (@143), DPTN2.5 (@143), DPTN2.5/3 (@143), DPTN2.5/4 (@143)	12-26	CU	2	—	600	20	B, C	2(115), 4
DPP-H2.5/ (@198)	12-28, Sol/Str	CU	2	—	300	20	B, D	2(115), 4, #20
					150	20	C	
DPT2.5/1P (@199)	12-26, Sol/Str	CU	2	—	600	20	B, C	2(115), 4, #20
DPT4(@143), DPT4/3(@143), DPT4/4(@143), DPTN4(@143), DPTN4/3(@143), DPTN4/4(@143)	10-24	Cu	2	—	600	30	B, C	2(115), 4
DPT6(@143), DPT6/3(@143), DPT6/4(@143), DPTN6(@143), DPTN6/3(@143), DPTN6/4(@143)	8-20	Cu	2	—	600	43	B, C	2(115), 4
DPT10 (@143), DPT10/3 (@143), DPTN10 (@143), DPTN10/3 (@143)	6-20	Cu	2	—	600	60	B, C	2(115), 4
DPTN16 (@143), DPTN16/3 (@143)	4-20	Cu	2	—	600	85	B, C	2(115), 4
DPTN35 (@143)	2-14	Cu	2	—	600	115	B, C	2(115), 4
MWX500-500 (@153), MWX500-508 (@153)	12-28 AWG (4-0.2 mm ²), SOL/STR	Cu	2	—	300	12	B	2(115), 4
					300	Note A	D	
MC900 (@154)	12-24 AWG	Cu	2	5	300	16	B	2(115), 4, #20
						Note A	D	
ME09 (@155)			1		300	16	B	2(115), 4, #20
						Note A	D	
DSPB2.5/ (@156)	12-28 AWG	Cu	2	-	300	-	B, C	2(115), 4, #20
					600	—	D	
DST2.5/1P-PE (@157)	12-28 AWG	Cu	2	-	600	-	B, C	2(115), 4, #20
DPP-H2.5/ (@200)	12-28, Sol/Str	Cu	2	—	300	—	B, D	2(115), 4, #20
					150	—	C	
DPT2.5/1P-PE (@199)	12-26, Sol/Str	Cu	2	—	600	—	B, C	2(115), 4, #20
DPTN35-PE (@143)	2-14 AWG	Cu	2	-	600	-	B, C	2(115), 4

MWX751 (@160)	16-24, Sol/Str	Cu	2	-	300	10	B, D	2(115), 4
					150	10	C	
BCM120(@162), BCM121(@162)	10-22, Sol/Str	Cu	2	7	600	37	B, C	2(115), 4
BCM120(@163), BCM121(@163)	10-22, Sol/Str	Cu	2	7	300	37	B	2(115), 4
						Note A	D	
MPX420-100, MPX410-100 (@164)	4-20 AWG	Cu	2	—	600	66	B, C	2(115), 4
MPX420-100A, MPX410-100A (@165)	4-20 AWG	Cu	2	—	300	66	B	2(115), 4
					150	66	C	
					300	Note A	D	
MPX313-750 (@166)	10-24 AWG	Cu	2	—	600	30	B, C	2(95), 4
MPX313-7504 (@167)	10-24 AWG	Cu	2	—	300	30	B	2(95), 4
					150	30	C	
					600	Note A	D	
MPX420-750 (@166)	8-24 AWG	Cu	2	—	600	36	B, C	2(115), 4
MPX420-7504 (@167)	8-24 AWG	Cu	2	—	300	36	B	2(115), 4
					150	36	C	
					600	Note A	D	
MPX410-750 (@166)	8-24 AWG	Cu	2	—	600	36	B, C	2(115), 4
MPX410-7504 (@167)	8-24 AWG	Cu	2	—	300	36	B	2(115), 4
					150	36	C	
					600	Note A	D	
MPX420-3504, MPX410-3504 (@167)	16-24	Cu	2	—	300	10	B, D	2(115), 4
MPX420-5004, MPX410-5004, MPX420-5084, MPX410-5084 (@167)	12-24	Cu	2	—	300	20	B	2(115), 4
					300	Note A	D	

MPX420-1004 (@167)	12-24	Cu	2	—	300	20	B, C	2(115), 4
					600	Note A	D	
MPX410-1505 (@186)	2-14	Cu	2	—	600	101	B, C	2(115), 4
CDK2.5V(@143)	12-24	CU	2	5	300	20	B, C	2(115), 4
					600	Note A	D	
CDK4V(@143)	10-22	CU	2	6	300	30	B, C	2(115), 4
					600	Note A	D	
OM49004 (@173)	14-28	CU	2	—	300	10	B, D	2(115), 4, #33
OM49005 (@173a)	—	CU	1	—	300	10	B, D	2(115), #33
OM49007 (@173)	14-28	CU	2	—	300 (##1)	10	B, D	2(115), 4, #33
OM49006 (@173b)	—	CU	1	—	300 (##1)	10	B, D	2(240), #33
MH160-016M (@174)	6-20	CU	2	13.2	300	57	B	2(115), 4
					150	57	C	
					300	Note A	D	
MH160-016M (@175); MH160-016M (@177)	6-20	CU	2	13.2	300	57	B,C	2(115), 4
					600	Note A	D	
MH160-016M (@176)	6-20	CU	2	13.2	300	57	B	2(115), 4
					300	Note A	D	
MPX232 (@178), MPX233 (@195)	12-28	Cu	2	—	300	20	B	2 (115), 4
						Note A	D	
MPX231 (@179)	12-28	Cu	2	—	300	15	B	2 (115), 4
						Note A	D	

MPX243 (@195), MPX242 (@196), MPX252 (@196)	14-28	Cu	2	—	300	15	B	2 (115), 4
						Note A	D	
MWX510 (@191), MWX511 (@191)	18 - 28	Cu	2	—	150	4	B	2(115), 4
MD511-500(@197)	12 - 28	Cu	2	4-6	300	10	B, D	2 (115), 4
MD332-500(@197)	—	—	1	—	300	10	B, D	2 (115)
MD022-500(@197)	—	—	2	—	300	10	B, D	2 (115)
MPC700-250(11)	20-26 sol/str	Cu	2	—	150	6	B	2(115), 4
MPE700-250(11)	—	—	2	—	150	6	B	2 (130)
MPE720-250(11)	—	—	2	—	150	6	C	2 (130)
DPTTB1.5	26-14 sol/str	Cu	2	—	600	15	B, C	2(115), 4
DPTTB2.5	28-12 sol/str	Cu	2	—	600	20	B, C	2(115), 4
DPTTB1.5-PE	26-14 sol/str	Cu	2	—	600	—	B, C	2(115), 4
DPTTB2.5-PE	28-12 sol/str	Cu	2	—	600	—	B, C	2(115), 4
MDC1(@201)	12-24 sol/str	Cu	2	—	300	16	B, D	2(115), 4, #34
MDC1(@202)	12-24 sol/str	Cu	2	—	600	20	B, C	2(115), 4, #34
MDC1(@210)	10-20 sol/str	Cu	2	—	600	25	B, C	2(115), 4, #34
MDE03(@203)	—	—	1	—	300	16	B, D	2(125), #34
MDE03(@204)	—	—	1	—	600	20	B, C	2(125), #34
MDE03(@211)	—	—	1	—	600	25	B, C	2(115), #34
MXC200(@206)	16-28 sol/str	Cu	2	—	300	10	B, D	2(115), 4, #35
MXE030(@207)	—	—	1	—	300	10	B	2(115), #35
MXE040(@207)	—	—	1	—	300	10	B, D	2(115), #35
MD (@208)	—	—	1	—	300	10	B	2(115), #35

Note A - These limited ratings are applicable to a terminal block for use in or with industrial control equipment whereby the load on any single circuit of the terminal block does not exceed 15 A at 51-150 V, 10 A at 151-300 V, or 5 A at 301-600 V, or the maximum ampere rating, whichever is less.

(1) May be followed by 381, 500, 508, 750, 762 or 952, followed by M2, M3 or O2.

(11) - Followed by pole count and an alphanumeric digit for commercial purposes

(1A) Followed by # or -, followed by 5.00, 500, E1, 5.08, 508, F1, 100, N1, followed by 02 thru 24, followed by one thru six alphanumeric digits or blank.

(1AA) Followed by # or -, followed by 5.00, 500, E1, 5.08, 508, F1, 100, N1, 7.62 or 762, followed by 02 thru 24, followed by one thru six alphanumeric digits or blank.

(1B) Followed by # or -, followed by 10.16, 016 or O1, followed by 02 thru 24, followed by one thru six alphanumeric digits or blank.

(1C) Followed by 350 or 381, followed by 02 thru 24, followed by one thru six alphanumeric digits or blank.

(1D) Followed by 500 or 508, followed by 02 thru 24, M02 thru M99 or M2 thru M99, followed by one thru six alphanumeric digits or blank.

(1E) Followed by 381, 500, 508, 750, 762 or 952, followed by 02 thru 24, M02 thru M99 or M2 thru M99, followed by one thru six alphanumeric digits or blank.

(1Ea) Followed by 952, followed by M, 02 thru 99, followed by 89, followed by one thru six alphanumeric digits or blank.

(1Eb) Followed by 381, 500 or 508, followed by 02 thru 24, M02 thru M99 or M2 thru M99, followed by one thru six alphanumeric digits or blank.

(1Ec) Followed by 750, 762 or 952, followed by 02 thru 24, M02 thru M99 or M2 thru M99, followed by one thru six alphanumeric digits or blank.

(1Ed) Followed by 952, followed by 02 thru 24, M02 thru M99 or M2 thru M99, followed by one thru six alphanumeric digits or blank.

(1F) Followed by 02 thru 24, M02 thru M99 or M2 thru M99, followed by one thru six alphanumeric digits or blank.

(2) Followed by 02 thru 24.

(2a) Followed by 02 thru 24, followed by one thru six alphanumeric digits or blank.

(3) Followed by 00, 01, 12 or 22, followed by 02 thru 12, followed by 1, 2, 3, A, B or C, followed by one thru six alphanumeric digits or blank.

(4) Followed by three alphanumeric digits, followed by 500, 508, 750, 762, 100 or 016, followed by 02 thru 24, followed by one thru six alphanumeric digits or blank.

(5) Followed by 000, followed by 350 or 508, followed by 02 thru 24, followed by one thru six alphanumeric digits or blank.

(6) Followed by 01 or 02, followed by 02 thru 24.

(7) Followed by -500, followed by M, followed by 02 thru 24.

(8) Followed by 500, followed by 02 thru 24.

(9) Followed by 02 thru 16.

(10) Followed by 02 thru 20.

(X1) Followed by 02 to 24.

(X2) May be followed by 0 to 8 alphanumeric digits.

(*) Terminal blocks have been subjected to a 30 min secureness test as part of the mechanical sequence outlined in UL486 E

(**) Solid wire only

(zz) Followed by 02 to 12 inclusive for number of contacts, and may be followed by 0 to 6 alphanumeric digits.

(z) Followed by 02 to 08 inclusive for number of contacts, and may be followed by 0 to 6 alphanumeric digits.

(#) When employing circuit jumpers, the spacers shall be used to maintain spacings between uninsulated live parts of opposite polarity.

(&) Tighten torque value for jumper screw as tabulated below.

Series No.	Torque, in-lbs (Nm)
CDU2.5N	5 (0.56)
CDU4N	6 (0.68)
CDU6N	6 (0.68)
CDU10N	6 (0.68)

(&1) Torque value 7 lb-in (0.8 N-m) for screw size M3.5; 12 lb-in (1.4 N-m) for screw size M4

#1 Screw covers have not been evaluated for suitability as electric barriers

#2 The Terminal Blocks provide printed circuit board edge connector and is intended use with 1.2 mm thick PWB, the suitability of the electrical connection (including spacings between PWB trace) shall be considered during the end-use product investigation.

#3 Model MC420 mated with ME230, MC420 mated with ME240, MC420 mated with ME250, MC420 mated with ME252, MC420 mated with ME260, MC420 mated with ME030, MC420 mated with ME040, OMC420 mated with ME030, OMC420 mated with ME040, MC421 mated with ME050, MC421 mated with ME060, OMC421 mated with ME050, OMC421 mated with ME060; MC100 mated with ME030; MC100 mated with ME040; MC100 mated with ME233; MC100 mated with ME243; MC110 mated with ME030; MC110 mated with ME040; MC110 mated with ME233; MC110 mated with ME243 Series are intended mating together to become a terminal block assembly. These devices have not been evaluated for use with any other mating combinations and have not been evaluated for interrupting the flow of Current by connecting or disconnecting the mating terminal block assembly.

#4 Model MC230 mated with ME010 Series are intended mating together to become a terminal block assembly. These devices have not been evaluated for use with any other mating combinations and have not been evaluated for interrupting the flow of Current by connecting or disconnecting the mating terminal block assembly.

#5 Model MC520 mated with ME030; MC520 mated with ME040; MC521 mated with ME030; MC521 mated with ME040; MC560 mated with ME030; MC560 mated with ME040; MC561 mated with ME030; MC561 mated with ME040 are intended mating together to become a terminal block assembly. These devices have not been evaluated for use with any other mating combinations and have not been evaluated for interrupting the flow of Current by connecting or disconnecting the mating terminal block assembly.

#6 Model MC420 mated with ME430 Series; MC420 mated with ME440 Series are intended mating together to become a terminal block assembly. These devices have not been evaluated for use with any other mating combinations and have not been evaluated for interrupting the flow of Current by connecting or disconnecting the mating terminal block assembly.

#7 Model MD212-500 mated with MD022-500 Series as tabulated below are intended mating together to become a terminal block assembly. These devices have not been evaluated for use with any other mating combinations and have not been evaluated for interrupting the flow of Current by connecting or disconnecting the mating terminal block assembly.

Plug, Series No.	Header, Series No.
MD212-500XXE	MD022-500XX
MD212-500XXXa	MD022-500XXXa

#8 These models have been evaluated for its suitability as protective conductor terminal blocks and complies with the applicable grounding requirements for terminals for use in a protective circuit.

#9 Models MC100 mated with ME110, MC100 mated with ME120, MC100 mated with ME210, MC100 mated with ME220, MC200 mated with ME110, MC200 mated with ME120, MC200 mated with ME130, MC200 mated with ME140, MC200 mated with ME210, MC200 mated with ME220, MC200 mated with ME230, MC200 mated with ME240, MC201 mated with ME150, MC201 mated with ME160, MC201 mated with ME250, MC201 mated with ME260, MC310 mated with ME110, MC310 mated with ME120, MC310 mated with ME130, MC310 mated with ME140, MC310 mated with ME210, MC310 mated with ME220, MC310 mated with ME230, MC310 mated with ME240, MC311 mated with ME150, MC311 mated with ME160, MC311 mated with ME250, MC311 mated with

ME260 are intended mating together to become a terminal block assembly. These devices have not been evaluated for use with any other mating combinations and have not been evaluated for interrupting the flow of Current by connecting or disconnecting the mating terminal block assembly.

#10 Models MC420-381 mated with ME530-381, MC420-381 mated with ME540-381, MC421-381 mated with ME550-381, MC421-381 mated with ME560-381 are intended mating together to become a terminal block assembly. These devices have not been evaluated for use with any other mating combinations and have not been evaluated for interrupting the flow of Current by connecting or disconnecting the mating terminal block assembly.

#11 Models MC520-381 mated with ME530-381, MC520-381 mated with ME540-381, MC521-381 mated with ME550-381, MC521-381 mated with ME560-381, MC560-381 mated with ME530-381, MC560-381 mated with ME540-381, MC561-381 mated with ME550-381, MC561-381 mated with ME560-381 are intended mating together to become a terminal block assembly. These devices have not been evaluated for use with any other mating combinations and have not been evaluated for interrupting the flow of Current by connecting or disconnecting the mating terminal block assembly.

#12 Models MC700-500 mated with ME710-500, MC700-500 mated with ME720-500, MC700-500 mated with ME735-500, MC700-500 mated with ME745-500, MC705-500 mated with ME710-500, MC705-500 mated with ME720-500, MC705-500 mated with ME735-500, MC705-500 mated with ME745-500, MC705-500 mated with ME730-500, MC705-500 mated with ME740-500, MC700-100 mated with ME710-100, MC700-100 mated with ME720-100, MC705-100 mated with ME710-100, MC705-100 mated with ME720-100, MC705-100 mated with ME730-100, MC705-100 mated with ME740-100 are intended mating together to become a terminal block assembly. These devices have not been evaluated for use with any other mating combinations and have not been evaluated for interrupting the flow of Current by connecting or disconnecting the mating terminal block assembly.

#13 Models MC600-350 mated with ME910-350, MC600-350 mated with ME920-350, MC601-350 mated with ME950-350, MC601-350 mated with ME960-350, MC605-350 mated with ME930-350, MC605-350 mated with OME940-350, OMC600-350 mated with OME910-350, OMC600-350 mated with OME920-350, OMC601-350 mated with OME950-350, OMC601-350 mated with OME960-350, OMC605-350 mated with OME930-350, OMC605-350 mated with OME940-350 Series are intended mating together to become a terminal block assembly. These devices have not been evaluated for use with any other mating combinations and have not been evaluated for interrupting the flow of Current by connecting or disconnecting the mating terminal block assembly.

#14 Models OM15009-762 mated with OM15010-762 Series are intended mating together to become a terminal block assembly. These devices have not been evaluated for use with any other mating combinations and have not been evaluated for interrupting the flow of Current by connecting or disconnecting the mating terminal block assembly.

#15 Models MC101-762 mated with ME050-762 Series are intended mating together to become a terminal block assembly. These devices have not been evaluated for use with any other mating combinations and have not been evaluated for interrupting the flow of Current by connecting or disconnecting the mating terminal block assembly.

#16 Model MC200-750 mated with ME010-750, ME020-750, ME030-750 or ME040-750; MC201-750 mated with ME050-750 or ME060-750; MC310-508 mated with ME630-508 Series are intended mating together to become a terminal block assembly. These devices have not been evaluated for use with any other mating combinations and have not been evaluated for interrupting the flow of current by connecting or disconnecting the mating terminal block assembly.

#17 Model 15264 mated with 15265 Series are intended mating together to become a terminal block assembly. These devices have not been evaluated for use with any other mating combinations and have not been evaluated for interrupting the flow of Current by connecting or disconnecting the mating terminal block assembly.

#18 Models MC700-250 mated with ME730-250, MC700-250 mated with ME740-250, MC700-254 mated with ME730-254, MC700-254 mated with ME740-254, MC700-350 mated with ME730-350, MC700-350 mated with ME740-350, MC705-350 mated with ME730-350, MC705-350 mated with ME740-350, MC700-381 mated with ME730-381, MC700-381 mated with ME740-381, MC705-381 mated with ME730-381, MC705-381 mated with ME740-381 Series are intended mating together to become a terminal block assembly. These devices have not been evaluated for use with any other mating combinations and have not been evaluated for interrupting the flow of Current by connecting or disconnecting the mating terminal block assembly.

#19 Model MD012-500M mated with MD022-500 Series are intended mating together to become a terminal block assembly. These devices have not been evaluated for use with any other mating combinations and have not been evaluated for interrupting the flow of Current by connecting or disconnecting the mating terminal block assembly.

#20 These plugs and sockets as tabulated below are intended mating together to become a terminal block assembly. These devices have not been evaluated for use with any other mating combinations and have not been evaluated for interrupting the flow of Current by connecting or disconnecting the mating terminal block assembly.

Plug Series

Socket Series

MPC300-500, MPC300H-500, MXC200-500	ME010-500, ME020-500, ME030-500, ME040-500, ME010-100, ME020-100, ME030-100, ME040-100
MPC300-508, MPC300H-508, MXC200-508	ME010-508, ME020-508, ME030-508, ME040-508, ME010-016, ME020-016, ME030-016, ME040-016
MPC301-500, MPC301H-500	ME050-500, ME060-500, ME070-500, ME080-500, ME050-100, ME060-100, ME070-100, ME080-100
MPC301-508, MPC301H-508	ME050-508, ME060-508, ME070-508, ME080-508, ME050-016, ME060-016, ME070-016, ME080-016
MPC300-750	ME010-750, ME020-750, ME030-750, ME040-750
MPC301-750	ME050-750, ME060-750, ME070-750, ME080-750
MPC300-762	ME010-762, ME020-762, ME030-762, ME040-762
MPC301-762	ME050-762, ME060-762, ME070-762, ME080-762
MDC210-500	ME020-500, ME040-500
MC100, MC200, MC210 (with pitch 5.0 mm)	ME010-500, ME020-500, ME030-500, ME040-500, ME010-100, ME020-100, ME030-100, ME040-100
MC101, MC201, MC211 (with pitch 5.0 mm)	ME050-500, ME060-500, ME070-500, ME080-500, ME050-100, ME060-100, ME070-100, ME080-100
MC100, MC200, MC210 (with pitch 5.08 mm)	ME010-508, ME020-508, ME030-508, ME040-508, ME010-016, ME020-016, ME030-016, ME040-016
MC101, MC201, MC211 (with pitch 5.08 mm)	ME050-508, ME060-508, ME070-508, ME080-508, ME050-016, ME060-016, ME070-016, ME080-016
MC100, MC200, MC210 (with pitch 10.0 mm)	ME010-500, ME020-500, ME030-500, ME040-500, ME010-100, ME020-100, ME030-100, ME040-100
MC101, MC201, MC211 (with pitch 10.0 mm)	ME050-500, ME060-500, ME070-500, ME080-500, ME050-100, ME060-100, ME070-100, ME080-100
MC100, MC200, MC210 (with pitch 10.16 mm)	ME010-508, ME020-508, ME030-508, ME040-508, ME010-016, ME020-016, ME030-016, ME040-016
MC101, MC201, MC211 (with pitch 10.16 mm)	ME050-508, ME060-508, ME070-508, ME080-508, ME050-016, ME060-016, ME070-016, ME080-016
MC900	ME09
DSPB2.5/	DST2.5/1P-PE
MPC310-350, MPC311-350, MPC370-350	ME230-350, ME240-350, ME250-350, ME252-350, ME260-350, ME030-350, ME040-350, ME050-350, ME060-350
MPC310-381, MPC311-381	ME230-381, ME240-381, ME250-381, ME252-381, ME260-381, ME030-381, ME040-381, ME050-381, ME060-381
MPC310-350, MPC311-350	ME233-350, ME243-350, ME253-350, ME263-350
MPC350-350	MPE930-350, MPE940-350
MPC351-350	MPE931-350, MPE941-350, MPE931H-350, MPE941H-350
DPP-H2.5/	DPT2.5/1P
DPP-H2.5/	DPT2.5/1P-PE

#21 Model MZ700-500 mated with MC700-500 Series are intended mating together to become a terminal block assembly. These devices have not been evaluated for use with any other mating combinations and have not been evaluated for interrupting the flow of Current by connecting or disconnecting the mating terminal block assembly.

#22 Model MZ701-500 mated with MC700-500 Series are intended mating together to become a terminal block assembly. These devices have not been evaluated for use with any other mating combinations and have not been evaluated for interrupting the flow of Current by connecting or disconnecting the mating terminal block assembly.

#23 The terminal blocks consist of two halves with plug consisting of the push-in type terminals and socket consisting of the soldering terminals. These devices have not been evaluated to make or break the flow of current. These devices as tabulated below are not evaluated for use with any other mating connectors.

Plug Series	Socket Series
MPC300	ME030
MPC301	ME050

#24 Model MC mated with ME Series are intended mating together to become a terminal block assembly. These devices have not been evaluated for use with any other mating combinations and have not been evaluated for interrupting the flow of Current by connecting or disconnecting the mating terminal block assembly.

#25 600V when mounted on a suitably insulated mounting surface.

#26 These terminal blocks Cat. No. BCM101 Series are suitable for general industrial application when mounted on a suitably insulated mounting surface.

#27 Models MD512-500 mated with MD122-500 Series are intended mating together to become a terminal block assembly. These devices have not been evaluated for use with any other mating combinations and have not been evaluated for interrupting the flow of Current by connecting or disconnecting the mating terminal block assembly.

#28 Models MPZ100 mated with MF300 Series are intended mating together to become a terminal block assembly. These devices have not been evaluated for use with any other mating combinations and have not been evaluated for interrupting the flow of Current by connecting or disconnecting the mating terminal block assembly.

#29 These terminal blocks are suitable for general industrial (such as motor controllers, pushbutton stations, etc.) application when with voltage rating up to 300 V and mounted on a suitably insulated mounting surface.

#30 These terminal blocks are suitable for 600 V only when with Industrial control devices having limited ratings application and mounted on a suitably insulated mounting surface.

#31 Models MC420 mated with ME630 Series are intended mating together to become a terminal block assembly. These devices have not been evaluated for use with any other mating combinations and have not been evaluated for interrupting the flow of Current by connecting or disconnecting the mating terminal block assembly.

#32 Models MC421 mated with ME631 Series are intended mating together to become a terminal block assembly. These devices have not been evaluated for use with any other mating combinations and have not been evaluated for interrupting the flow of Current by connecting or disconnecting the mating terminal block assembly.

#33 Models OM49004 mated with OM49005 Series are intended mating together to become a terminal block assembly. Models OM49006 mated with OM49007 Series are intended mating together to become a terminal block assembly. These devices have not been evaluated for use with any other mating combinations and have not been evaluated for interrupting the flow of Current by connecting or disconnecting the mating terminal block assembly.

#34 Models MDC1 mated with MDE03 Series are intended mating together to become a terminal block assembly. These devices have not been evaluated for use with any other mating combinations and have not been evaluated for interrupting the flow of Current by connecting or disconnecting the mating terminal block assembly.

#35 Models MXC200 mated with MXE030, MXE040 and MD Series are intended mating together to become a terminal block assembly. These devices have not been evaluated for use with any other mating combinations and have not been evaluated for interrupting the flow of Current by connecting or disconnecting the mating terminal block assembly.

@ May be followed by 02-26 to indicate number of poles.

@1 Followed by 02 or 03.

- @1a Followed by 02 or 03, followed by one thru six alphanumeric digits or blank.
- @1b Followed by 02 or 03 thru 99, followed by one thru six alphanumeric digits or blank.
- @2 Followed by 100, followed by 02 through 14, followed by one thru six alphanumeric digits or blank.
- @3 Followed by DA, DB, DC, DD or DE.
- @4 Followed by 350 or 381, followed by 02 through 24, followed by one thru six alphanumeric digits or blank.
- @5 Followed by D or 381, followed by 02 through 18, followed by one thru six alphanumeric digits or blank.
- @6 Followed by 500 or 508, followed by 02 through 05, followed by one thru six alphanumeric digits or blank.
- @7 Followed by 381, followed by 02 through 20.
- @7a Followed by -381, followed by 02 through 20, followed by one thru six alphanumeric digits or blank.
- @8 Followed by 100, followed by M or blank, followed by 02 or 03, followed by one thru eight alphanumeric digits or blank.
- @9 Followed by 350, followed by M or blank, followed by 02 or 03, followed by one thru eight alphanumeric digits or blank.
- @10 Followed by 381, followed by A or B, followed by M or blank, followed by 02 thru 17, followed by one thru eight alphanumeric digits or blank.
- @11 Followed by 500 or 508, followed by A, B, AM, BM, MA or MB, followed by 02 or 03, followed by B, E, G, K, O, P, R, W, Y or blank , followed by one thru eight alphanumeric digits or blank.
- @12 Followed by 500 or 508, followed by AM, MA or A, followed by 02 or 03, followed by B, E, G, K, O, P, R, W, Y or blank , followed by one thru eight alphanumeric digits or blank.
- @13 Followed by 500 or 508, followed by M or blank, followed by 02 or 03, followed by one thru eight alphanumeric digits or blank.
- @14 Followed by 381, followed by 02 thru 10.
- @15 Followed by 500, followed by M, followed by 02 or 03, followed by one thru six alphanumeric or blank.
- @15a Followed by 500, followed by 02 thru 24, followed by one thru six alphanumeric or blank.
- @16 Followed by 381, 500, 508, 750, 762, 952, 100 or 016, followed by 02 thru 24, M02 thru M99 or M2 thru M99, followed by W or blank, followed by one thru six alphanumeric digits or blank.
- @17 Followed by *, followed by E, 500, 508 or F, followed by 02-10.
- @18 Followed by 02 thru 08, followed by E.
- @19 Followed by 02 thru 08.
- @20 Followed by 02 thru 26, followed by H or HU.
- @20A Followed by 02 thru 26, followed by H.
- @21 Followed by 02 thru 24, followed by V or blank.
- @22 Followed by 5.00, 500, E1, 5.08, 508 or F1, followed by 02 or 03, followed by one thru six alphanumeric digits or blank.
- @23 Followed by 5.00, 500, E1, 5.08, 508 or F1, followed by 02 thru 06, followed by one thru six alphanumeric digits or blank.
- @24 Followed by 500 or 508, followed by 02 thru 24, followed by B, E, G, K, O, R, W, Y or blank, followed by 25 or blank, followed by one thru six alphanumeric digits or blank.
- @25 Followed by 500 or 508, followed by M or blank, followed by 04 or 06, followed by B, E, G, K, O, R, W, Y or blank, followed by one thru six alphanumeric digits or blank.
- @26 Followed by 500 or 508, followed by M or blank, followed by 08 or 12, followed by B, E, G, K, O, R, W, Y or blank, followed by one thru six alphanumeric digits or blank.
- @27 Followed by M4 or blank, followed by 02 thru 99, followed by G, K, R, Y, E, W, P, B or blank, followed by one thru six alphanumeric or blank.
- @28 Followed by 02, 03 or 04, followed by N, followed by K or E, followed by L or R, followed by one thru four alphanumeric digits or blank.

- @29 Followed by 02 thru 24, followed by one thru six alphanumeric digits or blank.
- @30 Followed by 04, 06, 08, 10, 12, 14, 16, 18, 20, 22, 24, 26, 28, 30, 32, 34, 36, 38, 40, 42, 44, 46 or 48.
- @31 May be followed by additional suffixes.
- @32 Followed by 02 thru 22, followed by B, E, K, G, O, R, W or blank, followed by one thru eight alphanumeric digits or blank.
- @33 Followed by 02, 04, 06, 08, 10, 12, 14, 16, 18, 20, 22, 24, 26, 28, 30, 32, 34, 36, 38 or 40, followed by one thru six alphanumeric digits or blank.
- @34 Followed by 02 thru 08.
- @35 Followed by 02 thru 16, followed by S1.
- @36 Followed by DA, DB, DC, DD or DE, followed by one thru six alphanumeric digits or blank.
- @37 Followed by 02 thru 12.
- @37a Followed by 02 thru 12, followed by one thru six alphanumeric digits or blank.
- @37b Followed by 02 thru 12, followed by TCO, followed by one thru six alphanumeric digits or blank.
- @38 Followed by 02 thru 24.
- @39 Followed by 0, 1 or 2, followed by 500, 508, 750, 762, 100 or 016, followed by 01 thru 99, followed by B, E, G, K, O, P, R, W, Y or blank.
- @40 Followed by M or blank, followed by 02 or 03, followed by B, E, G, K, O, R, W, Y or blank.
- @41 Followed by 02 thru 12.
- @42 Followed by 457, followed by 03 thru 10, followed by B, E, G, K, O, R, W or Y.
- @43 Followed by B or E, followed by M17, O17, M10, M38, O38, M3D or O3D, followed by 02 thru 30.
- @44 Followed by M, followed by 02 or 03, followed by B, E, K, O, R, W or blank, followed by 7001.
- @45 Deleted.
- @46 Followed by 02 thru 11, followed by B, E, K, G, O, R, W or blank, followed by A or B, followed by one thru eight alphanumeric digits or blank.
- @47 Followed by 350, followed by 02 thru 16, followed by E, EB, G, K, O, R, W or Y, followed by A0 or A1.
- @48 Followed by 02 thru 24, followed by B, E, G, K, O, R, W or blank, followed by C.
- @49 Followed by 02 thru 24, followed by B, E, G, K, O, R, W or blank, followed by D.
- @50 Followed by 02 thru 24, followed by B, E, G, K, O, R, W or blank.
- @51 Followed by 500 or 508, followed by M02 or M03, followed by B, G, K, O, R, W or blank.
- @52 Followed by 02 or 03, followed by B, E, G, K, O, R, W or Y.
- @53 Followed by E03, followed by 01, 02, 03 or 04, followed by BL, YW, RD, GY, GN, WH, OR, BK, PU or 01.
- @54 Followed by E04, followed by 01, 02, 03, 04 or 07, followed by BL, YW, RD, GY, GN, WH, OR, BK, PU, 01 or 02.
- @55 Followed by E05, followed by 01, 02, 03 or 04, followed by BL, YW, RD, GY, GN, WH, OR, BK, PU, 01 or 02.
- @56 Followed by E06, followed by 01, 02, 03, 04 or 05, followed by BL, YW, RD, GY, GN, WH, OR, BK, PU, 01 or 02.
- @57 Followed by E06, followed by 06, followed by BL, YW, RD, GY, GN, WH, OR, BK, PU, 01, 02 or 03.
- @58 Followed by E07 or E08, followed by 01, 02, 03 or 04, followed by BL, YW, RD, GY, GN, WH, OR, BK or PU.
- @59 Followed by MA, followed by 02 or 03, followed by B, E, G, K, O, P, R, W, Y or blank , followed by one thru eight alphanumeric digits or blank.
- @60 Followed by 500, followed by 02 thru 24, followed by B, E, G, K, O, P, R, Y or W.
- @61 Followed by 500, followed by M, followed by 02 or 03, followed by B, E, G, K, O, P, R, Y or W.
- @62 Followed by 500, followed by 02 thru 24, followed by B, E, G, K, O, P, R, Y or W.

@63 Followed by 500, followed by M, followed by 02 or 03, followed by B, E, G, K, O, P, R, Y or W.

@64 Followed by B, E, G, K, O, R, W or blank.

@65 Followed by 02 thru 24, followed by B, E, K, O, P, R, W, Y or blank, followed by one thru six alphanumeric digits or blank.

@66 Followed by 02 thru 24, followed by one thru six alphanumeric digits or blank.

@67 Followed by G, K, P, R, W, Y or blank, followed by one thru six alphanumeric digits or blank.

@68 Followed by 02 thru 24, followed by one alphanumeric digit or blank, followed by two alphanumeric digits or blank, followed by 01, 02, 03, 04 or one thru six alphanumeric digits or blank.

@69 Followed by 02, 04, 06, 08, 10, 12, 14, 16, 18, 20, 22, 24, 26, 28, 30, 32, 34, 36, 38, 40, 42, 44, 46 or 48, followed by B, E, G, K, O, R, W or Y, followed by four thru ten alphanumeric digits or blank.

@70 Followed by 01 thru 99 or 001 thru 999, followed by B, E, G, K, O, R, W or Y, followed by one thru ten alphanumeric digits or blank.

@71 Followed by 02 thru 08, followed by two alphanumeric digits or blank, followed by 01 or blank.

@72 Followed by 02 thru 22, followed by B, E, G, K, O, R, W, Y, or blank, followed by one thru six alphanumeric digits or blank.

@73 Followed by 02 thru 22, followed by one thru six alphanumeric digits or blank.

@74 Followed by 350, followed by 02 thru 24, followed by B, E, K, O, P, R, Y or blank.

@75 Followed by 00, 01 or 02, followed by 500, 508, 750, 762, 100 or 016, followed by 02 thru 30, followed by K, E, R, Y, B, O, P or blank, followed by four alphanumeric digits.

@76 Followed by 500, followed by M, followed by 02 or 03.

@77 Followed by 762, followed by 04 thru 20.

@78 Followed by 952, followed by M, followed by 02 or 03.

@79 Followed by 02 thru 24, followed by one thru four alphanumeric digits or blank.

@80 Followed by 1, 2, 4 or 5, followed by 02 thru 08, followed by one thru four alphanumeric digits or blank.

@81 Followed by 7 or 8, followed by 02 thru 08, followed by one thru four alphanumeric digits or blank.

@82 Followed by 1, 2, 4 or 5, followed by 02 or 03, followed by one thru four alphanumeric digits or blank.

@83 Followed by 7 or 8, followed by 02 or 03, followed by one thru four alphanumeric digits or blank.

@84 Followed by 350, followed by 02 thru 24, followed by B, E, K, O, P, R, Y or blank, followed by A.

@85 Followed by 02 thru 30.

@86 Followed by 02 thru 06.

@87 Followed by 02 thru 24, followed by one thru eight alphanumeric digits or blank.

@88 Followed by 0 or 2, followed by 500 or 508, followed by M, followed by A or B, followed by 06 or 09, followed by one thru four alphanumeric digits or blank.

@89 Followed by 0 or 2, followed by 500 or 508, followed by M, followed by A or B, followed by 04 or 06, followed by one thru four alphanumeric digits or blank.

@90 Followed by 0 or 2, followed by 500 or 508, followed by M, followed by A, B or C, followed by 02 or 03, followed by one thru four alphanumeric digits or blank.

@91 Followed by one thru eight alphanumeric digits or blank.

@92 Followed by 508, followed by 02 thru 08, followed by B, E, G, K, O, R, W or Y, followed by V or blank.

@93 Followed by 02 thru 08, followed by B, E, G, K, O, P, R, W or Y, followed by a.

@94 Followed by 016, 100, 500, 508, 750 or 762, followed by 02 thru 30, followed by five alphanumeric digits or blank.

@95 Followed by 7 or 8, followed by 02 thru 08, followed by one thru four alphanumeric digits or blank, followed by A.

@96 Followed by 02 thru 06, followed by T.

@97 Followed by 520, 560, 521 or 561, followed by 350, followed by 02 thru 20, followed by one thru five alphanumeric digits or blank.

@98 Followed by 040 or 060, followed by 350, followed by 02 thru 20, followed by one thru five alphanumeric digits or blank.

@99 Followed by 016, followed by M, followed by 1 or 2, followed by 02 thru 20, followed by one thru ten alphanumeric digits or blank.

@100 Followed by 016, followed by 1 or 2, followed by 02 thru 06, followed by one thru ten alphanumeric digits or blank.

@101 Followed by 02, followed by one thru eight alphanumeric digits or blank.

@102 Followed by 02 thru 12, followed by one thru eight alphanumeric digits or blank.

@103 Followed by 02 thru 99, followed by one thru six alphanumeric digits or blank.

@103a Followed by 02 thru 99, followed by 89 or blank, followed by one thru six alphanumeric digits or blank.

@104 Followed by 02 or 03, followed by B, K, O, P, R, W or blank, followed by one thru four alphanumeric digits or blank.

@105 Followed by 801 or 804, followed by 635, followed by M, followed by 02 thru 99, followed by B, E, K, O, P, R, or W, followed by one thru six alphanumeric digits or blank.

@106 Followed by 801 or 804, followed by 952, followed by M, followed by 02 thru 99, followed by B, E, K, O, P, R, or W, followed by one thru six alphanumeric digits or blank.

@107 Followed by 02 thru 99, followed by B, E, G, K, O, R, W, Y or blank, followed by one thru six alphanumeric digits or blank.

@108 Followed by 02 thru 08, followed by one thru six alphanumeric digits or blank.

@109 Followed by 500, 508, 750, 762, 100 or 016, followed by 02 thru 99, followed by one thru seven alphanumeric digits or blank.

@110 Followed by 500, followed by 02 thru 99, followed by one thru seven alphanumeric digits or blank.

@110a Followed by 500, followed by A or blank, followed by 02 thru 99, followed by one thru seven alphanumeric digits or blank.

@111 Followed by 381, followed by 02 thru 99, followed by one thru seven alphanumeric digits or blank.

@112 Followed by 508, followed by 02 thru 04, followed by one thru six alphanumeric digits or blank.

@113 Followed by 03 thru 10, followed by B, E, K, G, R, W or Y, followed by one thru six alphanumeric digits or blank.

@114 Followed by 02 thru 12, followed by one thru eight alphanumeric digits or blank.

@115 Followed by 02 or 03, followed by one thru six alphanumeric digits or blank.

@116 Followed by A, B, E or J, followed by M10, M11, M24, M25, M31, M33, M10, M3H, O3H, O31, O33, or S11, followed by 02 thru 12, followed by one thru six alphanumeric digits or blank.

@116a Followed by A, B, E or J, followed by M10, M11, M24, M25, M31, M33, M10, M3H, O3H, O31, O33, S11 or S1G, followed by 02 thru 12, followed by one thru six alphanumeric digits or blank.

@117 Followed by 381, followed by 02 thru 24, followed by B, E, G, K, O, W, R, Y or blank, followed by one thru six alphanumeric digits or blank.

@118 Followed by 381, followed by 02 thru 24, followed by B, E, G, K, O, W, R, Y or blank, followed by one thru six alphanumeric digits or blank.

@119 Followed by S or B, followed by 2.5, followed by 02 thru 99, followed by one thru eight alphanumeric digits or blank.

@120 Followed by T or P, followed by 2.5, followed by one thru eight alphanumeric digits or blank.

@121 Followed by 02 thru 99.

@122 Followed by B or E, followed M10, followed by M or blank, followed by 02 thru 12, followed by B, followed by one thru six alphanumeric digits or blank.

@123 Followed by A, K, R or W, followed M10, followed by M or blank, followed by 02 thru 12, followed by B, . followed by one thru six alphanumeric digits or blank.

@124 Followed by B or E, followed M3A or M60, followed by M or blank, followed by 02 thru 12, followed by B, followed by one thru six alphanumeric digits or blank.

@125 Followed by A, K, R or W, followed by M3A or M60, followed by M or blank, followed by 02 thru 12, followed by B, followed by one thru six alphanumeric digits or blank.

@126 Followed by 02 thru 24, followed by B, G, K, O, P, R, Y, W or blank, followed by four alphanumeric digits or blank.

@127 Followed by -500, -508, -750, -762, -100 or -016, followed by 02 thru 99, followed by one thru eight alphanumeric digits or blank.

@128 Followed by -500, -508, -750 or -762, followed by 02 thru 99, followed by J, followed by one thru eight alphanumeric digits or blank.

@129 Followed by one to six alphanumeric digits or blank.

@130 Followed by one to eight alphanumeric digits or blank.

@131 Followed by -250, followed by 02 thru 12, followed by one thru eight alphanumeric digits or blank.

@132 Followed by 02-15, followed by U, followed by 02-15, followed by 0-6 alphanumeric digits.

@133 Followed by 02 thru 22, followed by B, E, K, G, O, R, W or blank, followed by A, B or blank, followed by one thru eight alphanumeric digits or blank.

@134 Followed by 02 thru 11, followed by B, E, K, G, O, R, W or blank, followed by one thru eight alphanumeric digits or blank.

@135 Followed by -01 thru -99, followed by one thru six alphanumeric digits or blank.

@136 Followed by 02 thru 20.

@137 Followed by -02 thru -12, followed by one thru six alphanumeric digits or blank.

@138 Followed by -02 thru -18, followed by six alphanumeric digits or blank.

@139 Followed by 01 thru 15, followed by A or blank, followed by one thru six alphanumeric digits or blank.

@140 Followed by 02 or 03, followed by NV, followed by B, K, O, P, R, W or blank, followed by one thru six alphanumeric digits or blank.

@141 Followed by 350, followed by 02 through 40, followed by -1, followed by one thru eight alphanumeric digits or blank.

@142 Followed by 01 thru 99, followed by B, E, G, K, O, R, W or Y, followed by one thru ten alphanumeric digits or blank.

@143 Followed by one thru six alphanumeric digits or blank.

@144 Followed by 01 thru 15, followed by A or blank, followed by 1 thru 6 alphanumeric digits or blank.

@145 Followed by -D or -19, followed by one thru six alphanumeric digits or blank.

@146 Followed by 01, followed by one thru six alphanumeric digits or blank.

@147 Followed by 02 thru 12, followed by one thru six alphanumeric digits or blank.

@148 Followed by 02 or 03, followed by one thru six alphanumeric digits or blank.

@149 Followed by 02 thru 12, followed by A or blank, followed by one thru six alphanumeric digits or blank.

@150 Followed by 02 thru 20, followed by one thru six alphanumeric digits or blank.

@151 Followed by 02 thru 09, followed by one thru six alphanumeric digits or blank.

@152 Followed by 02 thru 08, followed by one thru six alphanumeric digits or blank.

@153 Followed by 02 thru 24, followed by one thru six alphanumeric digits or blank.

@154 Followed by -500, followed by 02, 03 or 04, followed by one thru six alphanumeric digits or blank.

@155 Followed by R or L, followed by -500, followed by 02, 03 or 04, followed by one thru six alphanumeric digits or blank.

@156 Followed by 1P thru 99P, followed by one thru six alphanumeric digits or blank.

@157 Followed by -D or -19, followed by one thru six alphanumeric digits or blank.

@158 Followed by D or 381, followed by 04 through 36, followed by one thru eight alphanumeric digits or blank.

@159 Followed by D or 381, followed by 02 through 40, followed by -1, followed by one thru eight alphanumeric digits or blank.

@160 Followed by 350, followed by 7 or 8, followed by 02 thru 24, followed by one thru six alphanumeric digits or blank.

@161 Followed by one thru eight alphanumeric digits or blank.

@162 Followed by 02 thru 12, followed by H, followed by V2, followed by A, B or blank, followed by one thru six alphanumeric digits or blank.

@163 Followed by 02 thru 12, followed by blank, followed by V2, followed by A, B or blank, followed by one thru six alphanumeric digits or blank.

@164 Followed by B, or C, followed by 02 thru 09, followed by one thru six alphanumeric digits or blank.

@165 Followed by 01 thru 09, followed by one thru six alphanumeric digits or blank.

@166 Followed by 7 or 8, followed by 02 thru 12, followed by one thru six alphanumeric digits or blank.

@168 Followed by 02, 04, 06, 08, 10, 12, 14, 16, 18, 20, 22, 24, 26, 28, 30, 32, 34, 36, 38 or 40, followed by -1, followed by one thru six alphanumeric digits or blank.

@169 Followed by 02 thru 24, followed by 85, followed by one thru six alphanumeric digits or blank.

@167 Followed by 01 thru 12, followed by one thru six alphanumeric digits or blank.

@170 Followed by 02 thru 06, followed by AF, followed by one thru six alphanumeric digits or blank.

@171 Followed by 01 thru 08, followed by one thru six alphanumeric digits or blank.

@172 Followed by 1 or 2, followed by 02 thru 08, followed by one thru six alphanumeric digits or blank.

@173 Followed by -26, followed by K, E, R, Y, B, O, P, BE or blank, followed by G or blank, followed by one thru six alphanumeric digits or blank.

@173a Followed by H or blank, followed by -26, followed by K, E, R, Y, B, O, P, BE or blank, followed by G or blank, followed by one thru six alphanumeric digits or blank.

@173b Followed by H, followed by -26, followed by K or BE, followed by G or blank, followed by one thru six alphanumeric digits or blank.

@174 Followed by 1 or 2, followed by 01 thru 99, followed by one thru six alphanumeric digits or blank.

@175 Followed by 4, followed by 01 thru 99, followed by one thru six alphanumeric digits or blank.

@176 Followed by 5, followed by 01 thru 99, followed by one thru six alphanumeric digits or blank.

@177 Followed by 7 or 8, followed by 01 thru 99, followed by one thru six alphanumeric digits or blank.

@178 followed by -500 or -508, followed by 02 thru 98, followed by one thru six alphanumeric digits or blank.

@179 Followed by -500 or -508, followed by 01 thru 50, followed by one thru six alphanumeric digits or blank.

@180a followed by 02 thru 24, followed by 04, followed by one thru six alphanumeric digits or blank.

@180b followed by 02 thru 12, followed by 04, followed by one thru six alphanumeric digits or blank.

@181 followed by 02 thru 24, followed by one thru six alphanumeric digits or blank.

@182 followed by 811, followed by 635, followed by 02 thru 99, followed by one thru six alphanumeric digits or blank.

@182a followed by 811, followed by 952, followed by 02 thru 99, followed by one thru six alphanumeric digits or blank.

@183 followed by 7, 8, A or B, followed by 01 thru 99, followed by one thru six alphanumeric digits or blank.

@184 followed by -B or -E, followed by O3P or M3P, followed by 02 thru 24, followed by one thru six alphanumeric digits or blank.

@185 followed by -A or -K, followed by O3P or M3P, followed by 02 thru 22, followed by one thru six alphanumeric digits or blank.

@186 followed by 01 thru 99, followed by one thru six alphanumeric digits or blank.

@187 followed by 350, followed by 02 through 20, followed by one thru six alphanumeric digits or blank.

@188 followed by H or blank, followed by 350, followed by 04 through 34, followed by one thru six alphanumeric digits or blank.

@189 followed by 02 thru 99, followed by one thru six alphanumeric or blank.

@190 followed by B, G, K, P, R, W, Y or blank, followed by one thru six alphanumeric digits or blank.

@191 followed by -250 or -254, followed by 01 thru 24, followed by one thru six alphanumeric digits or blank.

@192 followed by 500 or 100, followed by M, followed by 02 thru 99, followed by G1, O, E1 or blank, followed by V or blank, followed by one thru six alphanumeric digits or blank.

@193 followed by -500, followed by S, followed by 04 thru 48, followed by B, E, G, K, O, R, W, Y or blank, followed by one thru six alphanumeric digits or blank.

@194 followed by 02 thru 22, followed by VH, followed by one thru six alphanumeric digits or blank.

@195 followed by -500 or -508, followed by 03 thru 99, followed by one thru six alphanumeric digits or blank.

@196 followed by -500 or -508, followed by 02 thru 98, followed by one thru six alphanumeric digits or blank.

@197 followed by 02 thru 24, followed by one thru six alphanumeric digits or blank.

@198 followed by 01 thru 99, followed by one thru eight alphanumeric digits or blank.

@199 followed by one thru six alphanumeric digits or blank.

@200 followed by 01 thru 99, followed by YG, followed by one thru six alphanumeric digits or blank.

@201 followed by 0, 2 or 3, followed by 0 or 2, followed by 508, followed by 02 thru 24, followed by one thru six alphanumeric digits or blank.

@202 followed by 0, 2 or 3, followed by 0 or 2, followed by 635, followed by 02 thru 18, followed by one thru six alphanumeric digits or blank.

@203 followed by 0, 2 or 3, followed by 508, followed by 9 or A, followed by 02 thru 24, followed by one thru six alphanumeric digits or blank.

@204 followed by 0, 2 or 3, followed by 635, followed by 7 or 8, followed by 02 thru 18, followed by one thru six alphanumeric digits or blank.

@205 followed by 350, followed by 02 through 24, followed by one thru six alphanumeric digits or blank.

@206 followed by 350 or 381, followed by A or blank, followed by 02 thru 24, followed by one thru six alphanumeric digits or blank.

@207 followed by 350 or 381, followed by 02 thru 24, followed by one thru six alphanumeric digits or blank.

@208 followed by 023, followed by 350, followed by 02 thru 24, followed by S1, followed by one thru six alphanumeric digits or blank.

@209 followed by A or blank, followed by 02 thru 24, followed by one thru six alphanumeric digits or blank.

@210 followed by 0, followed by 0, followed by 762, followed by 02 thru 12, followed by one thru ten alphanumeric digits or blank.

@211 followed by 0 or 5, followed by 762, followed by 7 or 8, followed by 02 thru 12, followed by one thru ten alphanumeric digits or blank.

Note 1 - For Pole 2 thru Pole 4 of Cat. No. OTA3001, the wiring methods are as the following. The jumper for Pole 2 and Pole 3 will not be withdrawn during normal operation.

Wiring Method	Pole 2 front	Pole 3 front	Pole 4 front	Pole 2 back	Pole 3 and Pole 4 back
1	One unprepared conductor	N/A	One unprepared conductor	Soldering post	One prepared conductor
2	N/A	One unprepared conductor	One unprepared conductor	Soldering post	One prepared conductor

Note 2 - The terminal blocks are constructed end to end stackable design, which may be assembled 4 thru 99 poles. The suitability of the assembly shall be determined in the end-use investigation.

Note 3 - Usage group C, 150 V, when at least one spacer added into two of adjacent poles; Usage group C, 300 V and usage group D, 600 V, when at least two spacers added into two of adjacent poles; Usage group C, 600 V, when at least three spacers added into two of adjacent poles; When construed with spacer(s), the usage voltage shall be the lowest voltage for the varied combination.

Note 4- The terminal blocks are constructed end to end stackable design, which may be assembled 8 thru 48 poles. The suitability of the assembly shall be determined in the end-use investigation.

Note 5- The terminal blocks are constructed end to end stackable design, which may be assembled 16 thru 48 poles. The suitability of the assembly shall be determined in the end-use investigation.

Note 6 - MWX400-350 Series and Cat. Nos MWX400-35007A8101, MWX400-35007A8102: Usage group D, 600 V, when at least 5.00 mm spacer added into two of adjacent poles; MWX400-500 Series: Usage group D, 600 V, when at least 3.50 mm or 5.00 mm spacer added into two of adjacent poles; When construed with spacer(s), the usage voltage shall be the lowest voltage for the varied combination.

Marking: Company name or tradename "DECA" and catalog designation.

Last Updated on 2021-12-10

The appearance of a company's name or product in this database does not in itself assure that products so identified have been manufactured under UL's Follow-Up Service. Only those products bearing the UL Mark should be considered to be Certified and covered under UL's Follow-Up Service. Always look for the Mark on the product.

UL permits the reproduction of the material contained in the Online Certification Directory subject to the following conditions: 1. The Guide Information, Assemblies, Constructions, Designs, Systems, and/or Certifications (files) must be presented in their entirety and in a non-misleading manner, without any manipulation of the data (or drawings). 2. The statement "Reprinted from the Online Certifications Directory with permission from UL" must appear adjacent to the extracted material. In addition, the reprinted material must include a copyright notice in the following format: "© 2021 UL LLC"